

Ersatzteilliste - Bill of Materials				
	112646	AM 12 230V ACTIVE MONITOR		
	112814	AM 12 120V ACTIVE MONITOR		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
		Zubehör		Accessories & packing material
	358206	BEDIENUNGSANL. AM 12	1	owner's manual AM12
	357181	KABEL-NETZ EU 10A/250V		power cord Europe
US only	357182	KABEL-NETZ UL/CSA 13A/125V	1	power cord US
	358242	KRT. AM 12, M 12	1	carton
	358527	FALTEINLAGE AM 12, M 12	1	carton filler
	345156	SCHUTZHÜLLE 1160X1200X0,08	1	poly bag 1160x1200
		Mechanische Teile		Cabinet material
LA 01	330499	LA LFT 3008 C 300K30	1	woofer C300 K 30
LA 02	347489	LA HFT 3008 FT 300H	1	horn & driver
	334231	MEMBRANE FÜR HFT 3008		replacement diaphragm
	302745	DICHTG-SEGM LA 12"	4	gasket 12"
	358004	DICHTG-SEGM HORN 347489	1	gasket horn
	357795	GRIFF 173,7X149,1	1	handle
	343091	BEZ.SCHILD GRIFF DYNACORD	1	name plate handle
	358008	DICHTG-SEGM GRIFF 357795	1	gasket handle
	347189	HÜLSE-HOCHST. 19656.000.55	1	stand mount
	358009	DICHTG-SEGM HOCHSTÄNDER	1	gasket stand mount
	345694	FUSS-GUMMI 3133 M	8	rubber foot
	358090	SCHUTZG. AM12, M12	1	grille
	358468	ZUSCHN. 489X315 PPI 20	1	foam grille
	357796	BEZ.SCHILD D LOGO SW-SI	1	DYNACORD logo
US only	357167	RKT AM 12 120V	1	mains transformer 120V
	357165	NETZTRAFO-RINGKERN 230V		mains transformer 230V
	348309	WI-SO PTC K155 100GRAD	1	resistor ptc
	348341	FEDERLEISTE 3POL CE100-	1	connector female 3-pole
	358055	GEH. AM 12	1	enclosure assy AM12
US only	359615	AM 12 120V US	1	power module 120V US
	358240	VERSTÄRKER AM 12		power module 230V
B 010	341343	BUCHSE-SPEAKON-VIERECK 4POL	1	speaker socket 4-pole
CN100	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
JS500	357138	STECKER-KALTGERÄTE	1	mains connector
US only	302573	SICHER T 6.300 A/250V	1	fuse 6.3A slow blow
	302587	SICHER T 3.15 A 250V		fuse 3.15A slow blow
	353905	DK 11 GR/GR/RT B 6FL	3	knob rotary gr/rd
	353909	DK 11 GR/GR/GR B 6FL	3	knob rotary gr/gr
	358551	KABEL-KONFEKT 10POL 0.045M	1	ribbon cable 10-way
US only	359603	CHASSIS-BED AM 12 120V	1	front panel AM12 120V
	356007	CHASSIS-BED AM 12		front panel
	841958	PCBAR#AM 12	1	pcb assy 84195
CNE+	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CNE-	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CNS01	327779	STIFTLEISTE 3POL STL11S-1	1	connector male 3-pin

	112646	AM 12 230V ACTIVE MONITOR		
	112814	AM 12 120V ACTIVE MONITOR		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
CNS02	327779	STIFTELEISTE 3POL STL11S-1	1	connector male 3-pin
CNS03	327779	STIFTELEISTE 3POL STL11S-1	1	connector male 3-pin
CNS04	327779	STIFTELEISTE 3POL STL11S-1	1	connector male 3-pin
CN500	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CN501	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CN502	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CN503	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CN504	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CN601	348334	STIFTELEISTE 3POL MLSS	1	connector male 3-pin
CN602	344975	MESSERLST. 10POL	1	connector male 10-pin
CN800	344975	MESSERLST. 10POL	1	connector male 10-pin
C0500	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0501	357350	KO-EL 3900.000MF 50V	1	cap electrolytic 3900uF/50V
C0502	357350	KO-EL 3900.000MF 50V	1	cap electrolytic 3900uF/50V
C0503	357350	KO-EL 3900.000MF 50V	1	cap electrolytic 3900uF/50V
C0504	357350	KO-EL 3900.000MF 50V	1	cap electrolytic 3900uF/50V
C0505	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0506	356605	KO-FOL 0.100MF 250V 5%	1	cap mylar 100nF
C0507	356605	KO-FOL 0.100MF 250V 5%	1	cap mylar 100nF
C0508	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0509	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0510	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0511	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF
C0512	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0513	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0514	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0515	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0516	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0517	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF
C0518	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0600	351994	KO-KER 120.0PF 500V 2%	1	cap ceramic 120pF
C0601	351994	KO-KER 120.0PF 500V 2%	1	cap ceramic 120pF
C0602	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0603	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0604	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0605	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0606	356605	KO-FOL 0.100MF 250V 5%	1	cap mylar 100nF
C0607	356605	KO-FOL 0.100MF 250V 5%	1	cap mylar 100nF
C0608	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0609	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0610	327389	KO-FOL 220.000PF 100V 5%	1	cap mylar 220pF
C0611	301431	KO-FOL 0.100MF 160V 5%	1	cap mylar 100nF
C0612	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0613	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0614	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0616	341276	KO-FOL 0.012MF 100V 5%	1	cap mylar 12nF
C0617	341276	KO-FOL 0.012MF 100V 5%	1	cap mylar 12nF
C0619	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0620	327391	KO-FOL 1500.000PF 100V 5%	1	cap mylar 1500pF
C0621	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0623	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V

	112646	AM 12 230V ACTIVE MONITOR		
	112814	AM 12 120V ACTIVE MONITOR		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0624	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0625	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0626	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0627	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0628	301474	KO-EL 22.000MF 16V BIP	1	cap bip electr. 22uF/16V
C0629	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0630	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF
C0631	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF
C0632	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0633	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0634	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0635	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0636	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0637	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0638	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0639	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0640	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0641	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0642	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0643	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0644	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0645	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0646	330656	KO-FOL 2.200MF 100V 5%	1	cap mylar 2.2uF/100V
C0647	359055	KO-FOL 10.000MF 100V 5%	1	cap mylar 10.0uF/100V
C0648	359055	KO-FOL 10.000MF 100V 5%	1	cap mylar 10.0uF/100V
C0649	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0650	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0800	344077	KO-EL 330.000MF 35V	1	cap electrolytic 330uF/35V
C0801	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0802	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0803	301549	KO-KER 680.0PF K 500V 10%	1	cap ceramic 680pF
C0804	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0805	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0806	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0807	301543	KO-KER 330.0PF 500V 10%	1	cap ceramic 330pF
C0808	301543	KO-KER 330.0PF 500V 10%	1	cap ceramic 330pF
C0809	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0810	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0811	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0812	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0813	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0814	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0815	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0816	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0817	341276	KO-FOL 0.012MF 100V 5%	1	cap mylar 12nF
C0818	341276	KO-FOL 0.012MF 100V 5%	1	cap mylar 12nF
C0819	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0820	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0821	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0822	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0823	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V

	112646	AM 12 230V ACTIVE MONITOR		
	112814	AM 12 120V ACTIVE MONITOR		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0824	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0825	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0826	301543	KO-KER 330.0PF 500V 10%	1	cap ceramic 330pF
C0827	301543	KO-KER 330.0PF 500V 10%	1	cap ceramic 330pF
C0828	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0829	340244	KO-FOL 0.330MF 63V 5%	1	cap mylar 330nF
C0830	342935	KO-FOL 0.068MF 100V 5%	1	cap mylar 68nF
C0831	341276	KO-FOL 0.012MF 100V 5%	1	cap mylar 12nF
C0832	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C0833	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0834	300303	KO-FOL 1800.000PF 100V 5%	1	cap mylar 1800pF
C0835	344105	KO-FOL 0.027MF 100V 5%	1	cap mylar 27nF
C0836	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0837	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0838	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0839	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0840	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0841	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0842	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0843	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0844	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0845	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C0846	341276	KO-FOL 0.012MF 100V 5%	1	cap mylar 12nF
C0847	340244	KO-FOL 0.330MF 63V 5%	1	cap mylar 330nF
C0848	342935	KO-FOL 0.068MF 100V 5%	1	cap mylar 68nF
C0849	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0850	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
D0001	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0002	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0500	357143	DIODE MUR 420	1	diode MUR 420
D0502	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0503	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0504	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85
D0505	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0506	307916	DIODZ BZX 55C 7V5 0.50W	1	diode zener 7V5
D0507	307916	DIODZ BZX 55C 7V5 0.50W	1	diode zener 7V5
D0508	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0509	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0510	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0511	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0512	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0513	357143	DIODE MUR 420	1	diode MUR 420
D0515	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0516	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0600	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0601	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0602	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0603	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0604	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0605	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0606	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148

	112646	AM 12 230V ACTIVE MONITOR		
	112814	AM 12 120V ACTIVE MONITOR		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
D0607	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0608	307916	DIODZ BZX 55C 7V5 0.50W	1	diode zener 7V5
D0609	307916	DIODZ BZX 55C 7V5 0.50W	1	diode zener 7V5
D0610	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0611	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0612	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0613	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0614	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0615	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0616	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0617	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0618	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0619	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0620	329511	DIODZ BZX 55C 2V4 0.50W	1	diode zener 2V4
D0621	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0622	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0800	340243	LED RT 3MM LS 3369-EH	1	LED red 3mm
D0801	340243	LED RT 3MM LS 3369-EH	1	LED red 3mm
D0802	352093	LED GN 3MM LG 3369-EH	1	LED green 3mm
D0803	343785	DIODZ BZX 85C 27V 1.30W	1	diode zener 27V
E0600	354859	RELAIS 793-P-1C-S 24VDC	1	relay 24V
G0500	357140	GLRI GBU 8K	1	rectifier GBU 8k
G0501	357140	GLRI GBU 8K	1	rectifier GBU 8k
H0600	343456	DICKS-NETZW. 8PIN 2%	1	res.network 8x4.7k Ohm
H0601	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
I0500	357144	IC LM 319 COMPARATOR	1	IC LM 319
I0600	354199	IC SPNG.REG. LM 317 T	1	IC LM 317 voltage regulator
I0601	354929	IC SPNG.REG. LM 337 T	1	IC LM 337 voltage regulator
I0602	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0603	307421	IC CA 3080 E OTA	1	IC CA 3080 E
I0604	354919	IC OP 97 FP	1	IC OP 97
I0605	332985	IC TL 074 CN	1	IC TL 074 CN
I0606	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0607	349083	IC LM 3886 T	1	IC LM 3886 T
I0800	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0801	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0802	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0803	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0804	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0805	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
JS800	354000	BUCHSE-FL. XLR 3POL SW	1	connector XLR female 3-pole
JS801	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS802	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS803	357139	BUCHSE-CINCH 2X CINCH	1	cinch connector
L0600	348592	FILTERSP. 2.50UH/0.004OHM	1	coil 2.5uH
L0601	357080	FILTERSP. 599.00UH/ 0.46OHM	1	inductor 599 uH
Q0500	357142	TRANS IRF9Z 34 N P-CHAN	1	transistor IRF9Z 34 N
Q0501	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0502	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0503	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0504	348422	TRANS MPSA 42	1	transistor MPSA 42

	112646	AM 12 230V ACTIVE MONITOR		
	112814	AM 12 120V ACTIVE MONITOR		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
Q0505	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0506	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0507	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0508	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0509	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0510	357141	TRANS IRFZ 34 N N-CHAN	1	transistor IRFZ 34 N
Q0511	331657	TRANS MJ 15022	1	transistor MJ 15022
Q0512	331657	TRANS MJ 15022	1	transistor MJ 15022
Q0513	348409	TRANS 2SC 4793	1	transistor 2SC 4793
Q0514	331658	TRANS MJ 15023	1	transistor MJ 15023
Q0515	331658	TRANS MJ 15023	1	transistor MJ 15023
Q0600	328887	TRANS MJE 15030	1	trans. MJE 15030
Q0601	328888	TRANS MJE 15031	1	trans. MJE 15031
Q0602	338869	TRANS MJE 350	1	transistor MJE 350
Q0603	338868	TRANS MJE 340	1	transistor MJE 340
Q0604	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0605	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0606	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0607	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0608	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0609	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0610	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0611	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0612	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0613	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0614	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0615	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0616	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0617	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0618	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0619	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0620	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0621	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0622	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0623	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0624	307911	TRANS BF 393	1	transistor BF 391
Q0625	307911	TRANS BF 393	1	transistor BF 391
Q0626	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0627	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0628	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0629	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0630	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0631	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25
Q0632	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0633	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0634	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0635	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0636	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25
Q0637	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0638	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0639	306928	TRANS BC 560 C	1	transistor BC 560 C

	112646	AM 12 230V ACTIVE MONITOR		
	112814	AM 12 120V ACTIVE MONITOR		
Pos. Nr.	Best. Nr.		Menge	
Ref. No.	Part No.	Bezeichnung	Qty	Description
Q0640	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0641	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25
Q0642	330264	TRANS J 111	1	transistor J 111 A
Q0643	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0644	335763	TRANS 2N 3904	1	transistor 2N 3904
R0556	348490	WI-SO NTC 100.00 KOHM	1	safety component NTC
R0561	348456	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm 5watt
R0562	348456	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm 5watt
R0613	341713	WI-DR 4.70 OHM 4.00W 5%	1	resistor 4.70 Ohm 4watt
R0615	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt
R0668	348593	WI-SO NTC 2.20 KOHM	1	safety component NTC
R0671	348593	WI-SO NTC 2.20 KOHM	1	safety component NTC
R0759	357179	WI-DR 20.00 OHM 5.00W 5%	1	resistor 20 Ohm 5watt
R0760	357179	WI-DR 20.00 OHM 5.00W 5%	1	resistor 20 Ohm 5watt
R0761	357179	WI-DR 20.00 OHM 5.00W 5%	1	resistor 20 Ohm 5watt
VR600	348674	WI-TRI 250.00 OHM LIN	1	pot trim 250 Ohm lin
VR601	348486	WI-TRI 47.00 KOHM LIN	1	pot trim 47k Ohm lin
VR800	352325	P-DREH 10KOHM LIN	1	pot 10k B
VR801	352325	P-DREH 10KOHM LIN	1	pot 10k B
VR802	352325	P-DREH 10KOHM LIN	1	pot 10k B
VR803	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR804	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR805	352328	P-DREH 20KOHM LOG+	1	pot 20k log
V0600	357298	LAMPE-HALOGEN BEARB.AUS	1	protection bulb