

Ersatzteilliste - Bill of Materials				
	<b>112943</b>	<b>M 212 230V</b>		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
		<b>Zubehör</b>		<b>Accessories &amp; packing material</b>
	363476	BEDIENUNGSANL. M 212	1	owner's manual M 212
	362168	KABEL-NETZ EU 16A/250V	1	mains cable EURO
	337044	VERSCHL-KAPPE 2633 DP-437	1	plug, hole
	363288	KRT. M212	1	carton M 212
	345156	SCHUTZHÜLLE 1160X1200X0,08	1	poly bag 1160x1200
		<b>Mechanische Teile</b>		<b>Cabinet material</b>
LA001	360439	LA 12" ND12A	1	woofer ND12A
LA002	360439	LA 12" ND12A	1	woofer ND12A
	452399	LA REP-KIT ND12A/DL12ST		recone kit ND12A
LA003	361663	LA TREIBER ND 6-16	1	driver ND6-16
	452398	REPL.-KIT 16 OHM		replacement diaphragm
LA004	345799	LA HORN HP 8055	1	horn HP 8055
	344514	SCHALENGRIFF 209.6X173.7	2	handle EV #20265
	343091	BEZ.SCHILD GRIFF DYNACORD	2	name plate handle
	360529	DICHTG-SEGM GRIFF 344514	2	gasket for handle
	302745	DICHTG-SEGM LA 12"	8	gasket 12"
	360237	DICHTG-SEGM HORN HP 8055	1	gasket horn
	347189	HÜLSE-HOCHST. 19656.000.55	1	stand mount
	358009	DICHTG-SEGM HOCHSTÄNDER	1	gasket stand mount
	355141	FUSS KUNSTST. ABS SCHWARZ	8	plastic foot
	363286	SCHUTZG. M212	1	front grille M 212
	363287	ZUSCHN. 762X402 PPI20	1	grille foam
	357796	BEZ.SCHILD D LOGO SW-SI	1	DYNACORD logo
	362057	ZURRPUNKT 520153-21	1	rigging support
	349428	P-AIR.RIGGING 280 SW GEB.	2	rigging trace
	363281	GEH. M 212	1	enclosure M 212
	<b>363327</b>	<b>M 212 230V VERSTARKER</b>	<b>1</b>	<b>amp assy M 212 230V</b>
B0001	359273	BUCHSE-KALTGERÄTE POWER CON	1	connector mains in
B0002	362026	BUCHSE-KALTGERÄTE POWER CON	1	connector mains out
S0001	359274	SCHALTER-NETZ M.SIGNALLAMPE	1	switch, mains
	352556	DK 11,5 SW/WS C 6FL	1	knob black/white
	352559	DK 11,5 KAPPE BL/WS	1	cap blue/white
	330605	SICHER-HALTER	1	fuseholder
	330632	SICHER-HALTER-KAPPE	1	cap fuse holder
	302587	SICHER T 3.150 A/250V	1	fuse 3.15A slow blow
	352260	KABEL-KONFEKT 12POL 0.130M	1	ribbon cable assy 12-way
	363514	FRONTBL-BED M 212	1	front panel M 212
	362166	RKT M 15 120V/230V/240V	1	mains transformer M15
	348309	WI-SO PTC K155 100GRAD	1	resistor ptc
	348341	FEDERLEISTE 3POL CE100-	1	connector female 3-pole
	<b>842328</b>	<b>PCB M 212</b>	<b>1</b>	<b>pcb assy 84232</b>

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
CNAC1	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNAC2	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNAC3	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNAC4	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNGD1	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNGD2	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNL01	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNL02	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNL03	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNL04	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNL05	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNL06	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNPAR	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNS01	354306	STIFTLEISTE 16POL	0,5	connector male 16-pin
CNS02	358756	STIFTLEISTE 5POL STL11S-1	1	connector male 5-pin
CNS03	337395	STIFTLEISTE 6POL	1	connector male 6-pin
CNS04	336090	STIFTLEISTE 2POL	1	connector male 2-pin
CN001	348802	MESSERLST. 12POL	1	connector male 12-pin
CN002	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN003	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN004	344862	MESSERLST. 8POL	1	connector male 8-pin
CN005	344862	MESSERLST. 8POL	1	connector male 8-pin
CN006	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN007	344975	MESSERLST. 10POL	1	connector male 10-pin
CN008	344975	MESSERLST. 10POL	1	connector male 10-pin
CN009	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN010	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
C0001	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0002	359281	KO-KER 68.0PF 500V 2%	1	cap ceramic 68pF
C0003	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0004	337237	KO-FOL 0.047MF 100V 5%	1	cap mylar 47nF
C0005	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0006	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0007	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0008	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0009	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0010	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0011	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0012	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0013	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0014	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0015	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0016	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0017	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0018	340244	KO-FOL 0.330MF 63V 5%	1	cap mylar 330nF
C0019	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0020	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0021	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0022	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF
C0023	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0024	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0025	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0026	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF
C0027	326923	KO-FOL 3300.000PF 63V 5%	1	cap mylar 3300pF
C0028	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0030	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0031	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0032	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0033	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0034	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0035	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0036	327365	KO-EL 47.000MF 25V BIP	1	cap electr. bip 47uF/25V
C0037	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0038	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0039	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0040	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0041	332962	KO-EL 470.000MF 25V	1	cap electrolytic 470uF/25V
C0042	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0043	301458	KO-EL 2.200MF 63V	1	cap electrolytic 2.2uF/63V
C0044	337238	KO-FOL 0.680MF 63V 5%	1	cap mylar 680nF
C0045	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0046	342936	KO-FOL 0.150MF 63V 5%	1	cap mylar 150nF
C0047	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0048	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0049	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0050	332962	KO-EL 470.000MF 25V	1	cap electrolytic 470uF/25V
C0052	359282	KO-FOL 2700.000PF 250V 5%	1	cap mylar 2.7nF
C0053	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0054	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0055	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0056	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0057	359281	KO-KER 68.0PF 500V 2%	1	cap ceramic 68pF
C0058	359282	KO-FOL 2700.000PF 250V 5%	1	cap mylar 2.7nF
C0059	343533	KO-EL 220.000MF 25V	1	cap electrolytic 220uF/25V
C0061	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0062	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0063	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0064	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0065	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0066	359275	KO-EL 10000.00MF 63V	1	cap electr. 10000uF/63V
C0067	359275	KO-EL 10000.00MF 63V	1	cap electr. 10000uF/63V
C0068	359275	KO-EL 10000.00MF 63V	1	cap electr. 10000uF/63V
C0069	359275	KO-EL 10000.00MF 63V	1	cap electr. 10000uF/63V
C0070	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0071	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0072	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0073	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0074	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0075	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0076	301527	KO-KER 68.0PF K 500V 10%	1	cap ceramic 68pF
C0077	343533	KO-EL 220.000MF 25V	1	cap electrolytic 220uF/25V
C0080	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0081	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0082	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0083	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0084	342935	KO-FOL 0.068MF 100V 5%	1	cap mylar 68nF
C0085	357457	KO-FOL 1000.000PF 100V 5%	1	cap mylar 1nF
C0087	327389	KO-FOL 220.000PF 100V 5%	1	cap mylar 220pF
C0088	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0089	327389	KO-FOL 220.000PF 100V 5%	1	cap mylar 220pF
C0090	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0091	362061	KO-FOL 0.022MF 400V 5%	1	cap mylar 22nF/400V
C0092	362061	KO-FOL 0.022MF 400V 5%	1	cap mylar 22nF/400V
C0093	342933	KO-FOL 0.022MF 100V 5%	1	cap mylar 22nF
C0094	342933	KO-FOL 0.022MF 100V 5%	1	cap mylar 22nF
C0095	342933	KO-FOL 0.022MF 100V 5%	1	cap mylar 22nF
C0096	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0097	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0098	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0099	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0100	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0101	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0102	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0103	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0104	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0105	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0106	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0107	342933	KO-FOL 0.022MF 100V 5%	1	cap mylar 22nF
C0108	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0109	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0110	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0111	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0112	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0113	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0114	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0115	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0116	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0117	301474	KO-EL 22.000MF 16V BIP	1	cap bip electr. 22uF/16V
C0118	301474	KO-EL 22.000MF 16V BIP	1	cap bip electr. 22uF/16V
D0001	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0002	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0003	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0004	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0005	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0006	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0007	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0008	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0009	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0010	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0011	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0012	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0013	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0014	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0015	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0016	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0017	329511	DIODZ BZX 55C 2V4 0.50W	1	diode zener 2V4
D0018	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0019	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
D0020	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0021	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0022	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0023	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0024	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0025	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0027	341613	DIODZ BZX 55C 51V 0.50W	1	diode zener 51V 0,5watt
D0028	301310	DIODZ BZX 55C 20V 0.50W	1	diode zener 20V 0,5watt
D0029	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85
D0030	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0031	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0032	348389	DIODZ BZX 55C 13V 0.50W	1	diode zener ZPD 13V
D0033	348389	DIODZ BZX 55C 13V 0.50W	1	diode zener ZPD 13V
D0034	359280	DIODE MUR 1520	1	diode MUR 1520
D0035	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0036	359280	DIODE MUR 1520	1	diode MUR 1520
D0037	333733	DIODZ BZX 85C 12V 1.30W	1	diode zener 12V
D0038	309403	DIODZ BZX 55C 8V2 0.50W	1	diode zener ZPD 8V2
D0039	301309	DIODZ BZX 55C 10V 0.50W	1	diode zener ZPD 10V
D0040	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0041	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0042	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0043	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0044	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0045	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0046	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0047	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0048	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0049	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0050	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0051	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0052	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0053	329511	DIODZ BZX 55C 2V4 0.50W	1	diode zener 2V4
D0054	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0055	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0056	301310	DIODZ BZX 55C 20V 0.50W	1	diode zener 20V 0,5watt
D0057	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85
E0001	354859	RELAIS 793-P-1C-S 24VDC	1	relay 24V
E0002	356594	RELAIS 793-P-1A-S-TV10	1	relay 24V / spst
G0001	359277	GLRI GBU 12G 400V	1	rectifier GBU 12K
G0002	359277	GLRI GBU 12G 400V	1	rectifier GBU 12K
H0002	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0004	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0005	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
I0001	354199	IC SPNG.REGL. LM 317 T	1	IC LM 317 voltage regulator
I0002	354929	IC SPNG.REGL. LM 337 T	1	IC LM 337 voltage regulator
I0003	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0004	332985	IC TL 074 CN	1	IC TL 074 CN
I0005	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0006	307421	IC CA 3080 E OTA	1	IC CA 3080 E
I0007	354919	IC OP 97 FP	1	IC OP 97
I0008	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0009	330767	IC LM 311 P 1-F.VCOMP	1	IC LM 311

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
I0010	330767	IC LM 311 P 1-F.VCOMP	1	IC LM 311
I0011	349083	IC LM 3886 T	1	IC LM 3886 T
I0012	349083	IC LM 3886 T	1	IC LM 3886 T
I0013	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0014	332985	IC TL 074 CN	1	IC TL 074 CN
I0015	307421	IC CA 3080 E OTA	1	IC CA 3080 E
I0017	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0018	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0019	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0020	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0100	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
L0001	348592	FILTERSP. 2.50UH/0.004OHM	1	coil 2.5uH
Q0001	359283	TRANS 2SC 5200-0	1	transistor 2SC 5200
Q0002	359283	TRANS 2SC 5200-0	1	transistor 2SC 5200
Q0003	359283	TRANS 2SC 5200-0	1	transistor 2SC 5200
Q0004	348409	TRANS 2SC 4793	1	transistor 2SC 4793
Q0005	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25
Q0006	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0007	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0008	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0009	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0010	348408	TRANS 2SA 1837	1	transistor 2SA 1837
Q0011	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25
Q0012	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0013	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0014	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25
Q0015	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0016	348409	TRANS 2SC 4793	1	transistor 2SC 4793
Q0017	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0018	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0019	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0020	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0021	330264	TRANS J 111	1	transistor J 111 A
Q0022	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0023	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0024	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0025	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0026	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0027	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0028	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0029	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0030	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0031	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0032	348408	TRANS 2SA 1837	1	transistor 2SA 1837
Q0033	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0034	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0035	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0036	348409	TRANS 2SC 4793	1	transistor 2SC 4793
Q0037	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0038	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0039	359285	TRANS 2SA 1943-0	1	transistor 2SA 1943
Q0040	359285	TRANS 2SA 1943-0	1	transistor 2SA 1943
Q0041	359285	TRANS 2SA 1943-0	1	transistor 2SA 1943

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
Q0042	307430	TRANS BC 327-25 TO 92	1	transistor BC 327-25
Q0043	307430	TRANS BC 327-25 TO 92	1	transistor BC 327-25
Q0044	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0045	307911	TRANS BF 393	1	transistor BF 391
Q0046	307911	TRANS BF 393	1	transistor BF 391
Q0047	307912	TRANS BF 493 S TO 92	1	trans. BF 491
Q0048	307912	TRANS BF 493 S TO 92	1	trans. BF 491
Q0049	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0050	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0051	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0052	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0053	359423	TRANS HUF 75542 P3 N-CHAN	1	transistor HUF 75542
Q0054	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0055	359423	TRANS HUF 75542 P3 N-CHAN	1	transistor HUF 75542
Q0056	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0057	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0058	307430	TRANS BC 327-25 TO 92	1	transistor BC 327-25
Q0059	307430	TRANS BC 327-25 TO 92	1	transistor BC 327-25
Q0060	330264	TRANS J 111	1	transistor J 111 A
Q0061	301184	TRANS BC 550 C	1	transistor BC 550 B
RC007	337181	KO-FOL 0.010MF 100V 5%	1	cap mylar 10nF
RC009	359282	KO-FOL 2700.000PF 250V 5%	1	cap mylar 2.7nF
R0030	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0045	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0106	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt
R0107	341713	WI-DR 4.70 OHM 4.00W 5%	1	resistor 4.70 Ohm 4watt
R0110	348456	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm 5watt
R0114	348456	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm 5watt
R0117	348456	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm 5watt
R0137	358977	WI-SO NTC 12.00 KOHM	1	resistor ntc 12k Ohm
R0174	348593	WI-SO NTC 2.20 KOHM	1	safety component NTC
R0175	348593	WI-SO NTC 2.20 KOHM	1	safety component NTC
R0214	332306	WI-SCH 3.30 KOHM 2.00W 5%	1	resistor 3.3k Ohm 2watt
R0216	332306	WI-SCH 3.30 KOHM 2.00W 5%	1	resistor 3.3k Ohm 2watt
R0221	348550	WI-SO NTC 10.00 OHM K	1	resistor ntc 10 Ohm
S0001	327947	SCHALTELEMENT C42315-A1347-	0,125	switch element on/off
S0002	327947	SCHALTELEMENT C42315-A1347-	0,125	switch element on/off
VR001	348674	WI-TRI 250.00 OHM LIN	1	pot trim 250 Ohm lin
VR002	348486	WI-TRI 47.00 KOHM LIN	1	pot trim 47k Ohm lin
VR003	348486	WI-TRI 47.00 KOHM LIN	1	pot trim 47k Ohm lin
	<b>813638</b>	<b>PCB M 212 N 5</b>	<b>1</b>	<b>pcb assy 81363</b>
CN001	348802	MESSERLST. 12POL	1	connector male 12-pin
CN002	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN003	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
C0001	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0002	348846	KO-KER 680.0PF 500V 5%	1	cap ceramic 680pF
C0003	348846	KO-KER 680.0PF 500V 5%	1	cap ceramic 680pF
C0004	354958	KO-FOL 0.180MF 63V 5%	1	cap mylar 180nF
C0005	326675	KO-EL 100.000MF 10V BIP	1	cap bip electr. 100uF/10V
C0006	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0007	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0008	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0009	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0014	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0015	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0016	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0017	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0018	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0019	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0021	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0024	346841	KO-EL 47.000MF 16V	1	cap electrolytic 47uF/16V
C0039	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0040	354958	KO-FOL 0.180MF 63V 5%	1	cap mylar 180nF
C0043	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
D0001	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0002	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0003	352093	LED GN 3MM LG 3369-EH	1	LED green 3mm
D0004	340243	LED RT 3MM LS 3369-EH	1	LED red 3mm
D0005	352093	LED GN 3MM LG 3369-EH	1	LED green 3mm
D0006	340243	LED RT 3MM LS 3369-EH	1	LED red 3mm
D0007	357450	LED GE 3MM LY 3369-EH	1	LED yellow 3mm
D0012	357450	LED GE 3MM LY 3369-EH	1	LED yellow 3mm
D0020	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0021	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0022	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0023	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0024	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0025	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
H0001	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
I0001	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0002	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0003	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0004	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
JS001	357371	STECKER-FL. XLR 3POL PRINTB	1	connector XLR male 3-pin
JS002	359276	BUCHSE-COMBO XLR/KLINKE	1	connector XLR&phone jack
RC001	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
RC002	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
RC005	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
RC006	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
S0001	362038	SCHALTER-SCHIEBE 2XUM	1	switch slide
VR001	359303	P-DREH 50KOHM LOG-	1	pot 50k Ohm neg log