

		Ersatzteilliste - Bill of Materials		
	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
		Zubehör		Accessories & packing material
	363488	BEDIENUNGSANL. POWERMATE 2	1	owner's manual POWERMATE 2
	359436	KABEL-NETZ EU 10A/250V	1	mains cord EURO
	363815	QUICK START PM1000/1600-2	1	quick start POWERMATE 2
	363545	KRT. PM1600-2	1	carton PM1600-2
	363537	STYROPOR-EINL.LI.PM1000-2	1	styro foam left
	363538	STYROPOR-EINL.RE.PM1000-2	1	styro foam right
	338158	SCHUTZHÜLLE 800X1200X0,07	1	plastic bag
	363656	KRT. PM 1600-2 AUSSSEN	1	carton outer PM1600-2
		Mechanische Teile		Cabinet material
B 010	358992	BUCHSE-SPEACON-VIERECK 4POL	1	speacon connector 4-pol
B 020	358992	BUCHSE-SPEACON-VIERECK 4POL	1	speacon connector 4-pol
G 010	343270	GLRI GBPC 3504	1	rectifier GBPC-P 3504
G 020	343270	GLRI GBPC 3504	1	rectifier GBPC-P 3504
	353911	EINLEGEFOLIE POWERM.1000	1	mylar window
	353905	DK 11 GR/GR/RT B 6FL	22	knob rotary gr/rd
	353909	DK 11 GR/GR/SGR B 6FL	48	knob rotary gr/gre
	353910	DK 11 GR/GR/SW B 6FL	14	knob rotary gr/bla
	363541	DK 11 GR/GR/BL B 6FL	34	knob rotary gr/blu-gn
	353907	DK 11 GR/GR/CBL B 6FL	37	knob rotary gr/blu
	360319	DK 11 GR/GR/GR B 6FL	17	knob rotary l.gr/gr
	359946	SK 24X11 GR/SW 4X1,2	16	knob slide l.gr/blk
	363542	SK 24X11 RT/GR4X1,2	2	knob slide red
	363543	SK 24X11 CBL/GR 4X1,2	2	knob slide blue
	363544	SK 24X11 BLGN/GR 4X1,2	2	knob slide blue-green
	363113	SK 13X6,5 GR/SW 4X1,2	14	knob slide light-grey
	359999	TK 9,8X6 RT 3,3	19	knob switch red mid
	358363	TK 7,5X6 GR 3,3	31	knob switch l.gr small
	358360	TK 9,8X6 GR 3,3	27	knob switch l.gr mid
	359863	TK D2,8 SW 3,3	3	knob switch blk +48V
	363114	SEITENTEIL LI PM 1000-2	1	side wing left
	363115	SEITENTEIL RE PM 1000-2	1	side wing right
	363116	GRIFF LINKS PM 1000-2	1	handle left
	363117	GRIFF RECHTS PM 1000-2	1	handle right
	363487	FRONTBALKEN PM 1600-2	1	arm rest
	348415	LÜFTER TYP FBA08A24H DC	2	fan dc 24V
	341382	KNOPF-TASTE 20X8 SW 3.3	1	push button black
	349627	KABEL-KONFEKT 4POL 0.320M	1	ribbon cable assy 4-way
	346151	KABEL-KONFEKT 4POL 0.065M	1	ribbon cable assy 4-way
	362414	KABEL-KONFEKT-BUS 10POL 4X	1	bus cable 10-way
	362415	KABEL-KONFEKT-BUS 14POL 4X	1	bus cable 14-way
	354302	KABEL-KONFEKT 6POL 0.600M	1	ribbon cable 6-way
	355270	KABEL-KONFEKT 20POL 0.800M	1	ribbon cable assy 20-way
	363546	DECKEL-KPL PM1600-2	1	top cover assy PM1600-2
	355152	NIPPEL POWERMATE 1000	2	plastic nipple
	355151	SCHNAPPVERSCHLUSS SER.102	2	latch top cover

	112960	POWERMATE 1600-2 230V		
Pos. Nr.	Best. Nr.		Menge	
Ref. No.	Part No.	Bezeichnung	Qty	Description
	363480	FRONTBL-BED PM 1600-2	1	front panel PM1600-2
	363481	BODENSCHALE-BED PM 1600-2	1	chassis PM1600-2
	362384	RKT PM 1000/1600-2 120/230/	1	mains x-former 120/230/240V
	348341	FEDERLEISTE 3POL CE100-	2	connector female 3-pole
	813578	PCBDAR PM 1000-2	2	pcb assy 81357
CN001	344975	MESSERLST. 10POL	1	connector male 10-pin
CN003	349117	MESSERLST. 14POL	1	connector male 14-pin
C001A	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C001B	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C001C	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C001D	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C001E	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C001F	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C002A	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C002B	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C002C	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C002D	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C002E	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C002F	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C003A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C003B	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C003C	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C003D	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C003E	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C003F	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C004A	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C004B	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C004C	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C004D	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C004E	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C004F	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C005A	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C005B	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C005C	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C005D	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C005E	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C005F	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C006A	357453	KO-EL 1000.000MF 6.3V	1	cap elctrolytic 1000uF/6.3V
C006B	357453	KO-EL 1000.000MF 6.3V	1	cap elctrolytic 1000uF/6.3V
C006C	357453	KO-EL 1000.000MF 6.3V	1	cap elctrolytic 1000uF/6.3V
C006D	357453	KO-EL 1000.000MF 6.3V	1	cap elctrolytic 1000uF/6.3V
C006E	357453	KO-EL 1000.000MF 6.3V	1	cap elctrolytic 1000uF/6.3V
C006F	357453	KO-EL 1000.000MF 6.3V	1	cap elctrolytic 1000uF/6.3V
C007A	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C007B	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C007C	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C007D	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C007E	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C007F	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C008A	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V

	112960	POWERMATE 1600-2 230V				
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung			Menge Qty	Description
C008B	340522	KO-EL	10.000MF	35V	1	cap electrolytic 10uF/35V
C008C	340522	KO-EL	10.000MF	35V	1	cap electrolytic 10uF/35V
C008D	340522	KO-EL	10.000MF	35V	1	cap electrolytic 10uF/35V
C008E	340522	KO-EL	10.000MF	35V	1	cap electrolytic 10uF/35V
C008F	340522	KO-EL	10.000MF	35V	1	cap electrolytic 10uF/35V
C009A	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C009B	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C009C	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C009D	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C009E	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C009F	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C010A	335787	KO-KER	15.0PF	100V 2%	1	cap ceramic 15pF
C010B	335787	KO-KER	15.0PF	100V 2%	1	cap ceramic 15pF
C010C	335787	KO-KER	15.0PF	100V 2%	1	cap ceramic 15pF
C010D	335787	KO-KER	15.0PF	100V 2%	1	cap ceramic 15pF
C010E	335787	KO-KER	15.0PF	100V 2%	1	cap ceramic 15pF
C010F	335787	KO-KER	15.0PF	100V 2%	1	cap ceramic 15pF
C011A	335787	KO-KER	15.0PF	100V 2%	1	cap ceramic 15pF
C011B	335787	KO-KER	15.0PF	100V 2%	1	cap ceramic 15pF
C011C	335787	KO-KER	15.0PF	100V 2%	1	cap ceramic 15pF
C011D	335787	KO-KER	15.0PF	100V 2%	1	cap ceramic 15pF
C011E	335787	KO-KER	15.0PF	100V 2%	1	cap ceramic 15pF
C011F	335787	KO-KER	15.0PF	100V 2%	1	cap ceramic 15pF
C012A	357451	KO-KER	68.0PF	100V 2%	1	cap ceramic 68pF
C012B	357451	KO-KER	68.0PF	100V 2%	1	cap ceramic 68pF
C012C	357451	KO-KER	68.0PF	100V 2%	1	cap ceramic 68pF
C012D	357451	KO-KER	68.0PF	100V 2%	1	cap ceramic 68pF
C012E	357451	KO-KER	68.0PF	100V 2%	1	cap ceramic 68pF
C012F	357451	KO-KER	68.0PF	100V 2%	1	cap ceramic 68pF
C013A	357451	KO-KER	68.0PF	100V 2%	1	cap ceramic 68pF
C013B	357451	KO-KER	68.0PF	100V 2%	1	cap ceramic 68pF
C013C	357451	KO-KER	68.0PF	100V 2%	1	cap ceramic 68pF
C013D	357451	KO-KER	68.0PF	100V 2%	1	cap ceramic 68pF
C013E	357451	KO-KER	68.0PF	100V 2%	1	cap ceramic 68pF
C013F	357451	KO-KER	68.0PF	100V 2%	1	cap ceramic 68pF
C015A	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C015B	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C015C	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C015D	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C015E	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C015F	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C016A	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C016B	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C016C	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C016D	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C016E	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C016F	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C017A	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C017B	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C017C	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C017D	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF
C017E	336095	KO-FOL	0.100MF	63V 5%	1	cap mylar 100nF

	112960	POWERMATE 1600-2 230V		
Pos. Nr.	Best. Nr.		Menge	
Ref. No.	Part No.	Bezeichnung	Qty	Description
C017F	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C018A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C018B	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C018C	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C018D	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C018E	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C018F	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C019A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C019B	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C019C	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C019D	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C019E	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C019F	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C020A	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C020B	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C020C	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C020D	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C020E	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C020F	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C021A	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C021B	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C021C	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C021D	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C021E	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C021F	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C022A	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C022B	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C022C	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C022D	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C022E	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C022F	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C023A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C023B	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C023C	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C023D	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C023E	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C023F	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C024A	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C024B	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C024C	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C024D	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C024E	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C024F	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C025A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C025B	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C025C	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C025D	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C025E	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C025F	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C026A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C026B	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C026C	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C026D	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C026E	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C026F	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C027A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C027B	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C027C	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C027D	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C027E	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C027F	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C028A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C028B	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C028C	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C028D	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C028E	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C028F	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C029A	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C029B	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C029C	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C029D	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C029E	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C029F	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C030A	300303	KO-FOL 1800.000PF 100V 5%	1	cap mylar 1800pF
C030B	300303	KO-FOL 1800.000PF 100V 5%	1	cap mylar 1800pF
C030C	300303	KO-FOL 1800.000PF 100V 5%	1	cap mylar 1800pF
C030D	300303	KO-FOL 1800.000PF 100V 5%	1	cap mylar 1800pF
C030E	300303	KO-FOL 1800.000PF 100V 5%	1	cap mylar 1800pF
C030F	300303	KO-FOL 1800.000PF 100V 5%	1	cap mylar 1800pF
C031A	327393	KO-FOL 4700.000PF 63V 5%	1	cap mylar 4700pF
C031B	327393	KO-FOL 4700.000PF 63V 5%	1	cap mylar 4700pF
C031C	327393	KO-FOL 4700.000PF 63V 5%	1	cap mylar 4700pF
C031D	327393	KO-FOL 4700.000PF 63V 5%	1	cap mylar 4700pF
C031E	327393	KO-FOL 4700.000PF 63V 5%	1	cap mylar 4700pF
C031F	327393	KO-FOL 4700.000PF 63V 5%	1	cap mylar 4700pF
C032A	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C032B	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C032C	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C032D	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C032E	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C032F	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C033A	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C033B	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C033C	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C033D	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C033E	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C033F	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C034A	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C034B	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C034C	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C034D	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C034E	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C034F	336094	KO-FOL 6800.000PF 100V 5%	1	cap mylar 6800pF
C035A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V

	112960	POWERMATE 1600-2 230V			
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description	
C035B	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C035C	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C035D	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C035E	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C035F	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C036A	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF	
C036B	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF	
C036C	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF	
C036D	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF	
C036E	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF	
C036F	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF	
C037A	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF	
C037B	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF	
C037C	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF	
C037D	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF	
C037E	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF	
C037F	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF	
C038A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C038B	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C038C	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C038D	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C038E	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C038F	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C039A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C039B	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C039C	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C039D	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C039E	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C039F	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C040A	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF	
C040B	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF	
C040C	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF	
C040D	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF	
C040E	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF	
C040F	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF	
C041A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C041B	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C041C	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C041D	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C041E	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C041F	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C042A	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V	
C042B	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V	
C042C	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V	
C062A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C062B	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C062C	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C063A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C063B	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C063C	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C064A	356508	KO-KER 0.10MF 50V 20%	1	cap ceramic 100nF	
C064B	356508	KO-KER 0.10MF 50V 20%	1	cap ceramic 100nF	

	112960	POWERMATE 1600-2 230V				
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung			Menge Qty	Description
C064C	356508	KO-KER	0.10MF	50V 20%	1	cap ceramic 100nF
C065A	356508	KO-KER	0.10MF	50V 20%	1	cap ceramic 100nF
C065B	356508	KO-KER	0.10MF	50V 20%	1	cap ceramic 100nF
C065C	356508	KO-KER	0.10MF	50V 20%	1	cap ceramic 100nF
C066A	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C066B	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C066C	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C067A	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C067B	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C067C	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C068A	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C068B	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C068C	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C069A	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C069B	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C069C	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C081A	356508	KO-KER	0.10MF	50V 20%	1	cap ceramic 100nF
C081B	356508	KO-KER	0.10MF	50V 20%	1	cap ceramic 100nF
C081C	356508	KO-KER	0.10MF	50V 20%	1	cap ceramic 100nF
C081D	356508	KO-KER	0.10MF	50V 20%	1	cap ceramic 100nF
C081E	356508	KO-KER	0.10MF	50V 20%	1	cap ceramic 100nF
C081F	356508	KO-KER	0.10MF	50V 20%	1	cap ceramic 100nF
D001A	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D001B	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D001C	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D001D	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D001E	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D001F	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D002A	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D002B	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D002C	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D002D	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D002E	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D002F	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D003A	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D003B	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D003C	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D003D	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D003E	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D003F	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D004A	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D004B	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D004C	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D004D	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D004E	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D004F	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D005A	354003	LED RT	3MM	LOW CURRENT	1	led red
D005B	354003	LED RT	3MM	LOW CURRENT	1	led red
D005C	354003	LED RT	3MM	LOW CURRENT	1	led red
D005D	354003	LED RT	3MM	LOW CURRENT	1	led red
D005E	354003	LED RT	3MM	LOW CURRENT	1	led red
D005F	354003	LED RT	3MM	LOW CURRENT	1	led red

	112960	POWERMATE 1600-2 230V				
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung			Menge Qty	Description
D006A	301297	DIODE BAT 85	SCHOTTKY		1	diode BAT 85
D006B	301297	DIODE BAT 85	SCHOTTKY		1	diode BAT 85
D006C	301297	DIODE BAT 85	SCHOTTKY		1	diode BAT 85
D006D	301297	DIODE BAT 85	SCHOTTKY		1	diode BAT 85
D006E	301297	DIODE BAT 85	SCHOTTKY		1	diode BAT 85
D006F	301297	DIODE BAT 85	SCHOTTKY		1	diode BAT 85
D007A	354003	LED RT 3MM	LOW CURRENT		1	led red
D007B	354003	LED RT 3MM	LOW CURRENT		1	led red
D007C	354003	LED RT 3MM	LOW CURRENT		1	led red
D007D	354003	LED RT 3MM	LOW CURRENT		1	led red
D007E	354003	LED RT 3MM	LOW CURRENT		1	led red
D007F	354003	LED RT 3MM	LOW CURRENT		1	led red
D008A	354004	LED GN 3MM	LOW CURRENT		1	led green
D008B	354004	LED GN 3MM	LOW CURRENT		1	led green
D008C	354004	LED GN 3MM	LOW CURRENT		1	led green
D008D	354004	LED GN 3MM	LOW CURRENT		1	led green
D008E	354004	LED GN 3MM	LOW CURRENT		1	led green
D008F	354004	LED GN 3MM	LOW CURRENT		1	led green
D009A	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D009B	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D009C	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D009D	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D009E	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D009F	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D010A	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D010B	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D010C	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D010D	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D010E	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D010F	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D011A	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D011B	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D011C	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D011D	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D011E	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D011F	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D012A	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D012B	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D012C	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D012D	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D012E	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D012F	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D076A	357450	LED GE 3MM	LY 3369-EH		1	LED yellow 3mm
I001A	327197	IC NE 5532 P	2FACH OP		1	IC NE 5532 N
I001B	327197	IC NE 5532 P	2FACH OP		1	IC NE 5532 N
I001C	327197	IC NE 5532 P	2FACH OP		1	IC NE 5532 N
I001D	327197	IC NE 5532 P	2FACH OP		1	IC NE 5532 N
I001E	327197	IC NE 5532 P	2FACH OP		1	IC NE 5532 N
I001F	327197	IC NE 5532 P	2FACH OP		1	IC NE 5532 N
I002A	354933	IC NJM 2068 DD	DUAL IN		1	IC NJM 2068
I002B	354933	IC NJM 2068 DD	DUAL IN		1	IC NJM 2068
I002C	354933	IC NJM 2068 DD	DUAL IN		1	IC NJM 2068

	112960	POWERMATE 1600-2 230V			
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung		Menge Qty	Description
I003A	358898	IC MC 33178	2FACH OP	1	IC MC 33178
I003B	358898	IC MC 33178	2FACH OP	1	IC MC 33178
I003C	358898	IC MC 33178	2FACH OP	1	IC MC 33178
I004A	358898	IC MC 33178	2FACH OP	1	IC MC 33178
I004B	358898	IC MC 33178	2FACH OP	1	IC MC 33178
I004C	358898	IC MC 33178	2FACH OP	1	IC MC 33178
I005A	331340	IC TL 072 CP	2FACH OP	1	IC TL 072 CP
I005B	331340	IC TL 072 CP	2FACH OP	1	IC TL 072 CP
I005C	331340	IC TL 072 CP	2FACH OP	1	IC TL 072 CP
I006A	331340	IC TL 072 CP	2FACH OP	1	IC TL 072 CP
I006B	331340	IC TL 072 CP	2FACH OP	1	IC TL 072 CP
I006C	331340	IC TL 072 CP	2FACH OP	1	IC TL 072 CP
I007A	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I007B	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I007C	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I008A	343502	IC LM 2901 N		1	IC LM 2901
I008B	343502	IC LM 2901 N		1	IC LM 2901
I008C	343502	IC LM 2901 N		1	IC LM 2901
JS01A	354000	BUCHSE-FL. XLR 3POL	SW	1	connector XLR female 3-pole
JS01B	354000	BUCHSE-FL. XLR 3POL	SW	1	connector XLR female 3-pole
JS01C	354000	BUCHSE-FL. XLR 3POL	SW	1	connector XLR female 3-pole
JS01D	354000	BUCHSE-FL. XLR 3POL	SW	1	connector XLR female 3-pole
JS01E	354000	BUCHSE-FL. XLR 3POL	SW	1	connector XLR female 3-pole
JS01F	354000	BUCHSE-FL. XLR 3POL	SW	1	connector XLR female 3-pole
JS02A	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS02B	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS02C	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS02D	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS02E	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS02F	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS04A	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS04B	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS04C	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS04D	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS04E	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS04F	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
Q001A	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q001B	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q001C	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q001D	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q001E	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q001F	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q002A	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q002B	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q002C	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q002D	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q002E	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q002F	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q003A	348421	TRANS 2N 3906		1	transistor 2N 3906
Q003B	348421	TRANS 2N 3906		1	transistor 2N 3906
Q003C	348421	TRANS 2N 3906		1	transistor 2N 3906
Q003D	348421	TRANS 2N 3906		1	transistor 2N 3906

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
Q003E	348421	TRANS 2N 3906	1	transistor 2N 3906
Q003F	348421	TRANS 2N 3906	1	transistor 2N 3906
Q004A	348421	TRANS 2N 3906	1	transistor 2N 3906
Q004B	348421	TRANS 2N 3906	1	transistor 2N 3906
Q004C	348421	TRANS 2N 3906	1	transistor 2N 3906
Q004D	348421	TRANS 2N 3906	1	transistor 2N 3906
Q004E	348421	TRANS 2N 3906	1	transistor 2N 3906
Q004F	348421	TRANS 2N 3906	1	transistor 2N 3906
Q005A	348421	TRANS 2N 3906	1	transistor 2N 3906
Q005B	348421	TRANS 2N 3906	1	transistor 2N 3906
Q005C	348421	TRANS 2N 3906	1	transistor 2N 3906
Q005D	348421	TRANS 2N 3906	1	transistor 2N 3906
Q005E	348421	TRANS 2N 3906	1	transistor 2N 3906
Q005F	348421	TRANS 2N 3906	1	transistor 2N 3906
R100A	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R100B	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R100C	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R101A	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R101B	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R101C	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
S0001	354006	SCHALTER-RAST 2XUM	1	switch dpdt
S001A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S001B	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S001C	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S001D	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S001E	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S001F	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S002A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S002B	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S002C	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S002D	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S002E	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S002F	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S003A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S003B	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S003C	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S003D	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S003E	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S003F	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S004A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S004B	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S004C	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S004D	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S004E	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S004F	357446	SCHALTER-TAST 2XUM	1	switch dpdt
VR01A	362358	P-DREH 10KOHM LOG-	1	pot 10 k neg log
VR01B	362358	P-DREH 10KOHM LOG-	1	pot 10 k neg log
VR01C	362358	P-DREH 10KOHM LOG-	1	pot 10 k neg log
VR01D	362358	P-DREH 10KOHM LOG-	1	pot 10 k neg log
VR01E	362358	P-DREH 10KOHM LOG-	1	pot 10 k neg log
VR01F	362358	P-DREH 10KOHM LOG-	1	pot 10 k neg log
VR02A	352325	P-DREH 10KOHM LIN	1	pot 10k B

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
VR02B	352325	P-DREH 10KOHM LIN	1	pot 10k B
VR02C	352325	P-DREH 10KOHM LIN	1	pot 10k B
VR02D	352325	P-DREH 10KOHM LIN	1	pot 10k B
VR02E	352325	P-DREH 10KOHM LIN	1	pot 10k B
VR02F	352325	P-DREH 10KOHM LIN	1	pot 10k B
VR03A	352326	P-DREH 2X500KOHM LOG-	1	pot 2x500k C
VR03B	352326	P-DREH 2X500KOHM LOG-	1	pot 2x500k C
VR03C	352326	P-DREH 2X500KOHM LOG-	1	pot 2x500k C
VR03D	352326	P-DREH 2X500KOHM LOG-	1	pot 2x500k C
VR03E	352326	P-DREH 2X500KOHM LOG-	1	pot 2x500k C
VR03F	352326	P-DREH 2X500KOHM LOG-	1	pot 2x500k C
VR04A	352324	P-DREH 50KOHM LIN	1	pot 50k B
VR04B	352324	P-DREH 50KOHM LIN	1	pot 50k B
VR04C	352324	P-DREH 50KOHM LIN	1	pot 50k B
VR04D	352324	P-DREH 50KOHM LIN	1	pot 50k B
VR04E	352324	P-DREH 50KOHM LIN	1	pot 50k B
VR04F	352324	P-DREH 50KOHM LIN	1	pot 50k B
VR05A	352324	P-DREH 50KOHM LIN	1	pot 50k B
VR05B	352324	P-DREH 50KOHM LIN	1	pot 50k B
VR05C	352324	P-DREH 50KOHM LIN	1	pot 50k B
VR05D	352324	P-DREH 50KOHM LIN	1	pot 50k B
VR05E	352324	P-DREH 50KOHM LIN	1	pot 50k B
VR05F	352324	P-DREH 50KOHM LIN	1	pot 50k B
VR06A	362356	P-SHIB 10KOHM LOG+	1	fader 10k log
VR06B	362356	P-SHIB 10KOHM LOG+	1	fader 10k log
VR06C	362356	P-SHIB 10KOHM LOG+	1	fader 10k log
VR06D	362356	P-SHIB 10KOHM LOG+	1	fader 10k log
VR06E	362356	P-SHIB 10KOHM LOG+	1	fader 10k log
VR06F	362356	P-SHIB 10KOHM LOG+	1	fader 10k log
VR07A	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k
VR07B	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k
VR07C	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k
VR07D	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k
VR07E	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k
VR07F	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k
VR08A	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR08B	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR08C	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR08D	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR08E	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR08F	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR09A	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR09B	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR09C	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR09D	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR09E	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR09F	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR10A	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR10B	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR10C	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR10D	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR10E	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log

	112960	POWERMATE 1600-2 230V		
Pos. Nr.	Best. Nr.		Menge	
Ref. No.	Part No.	Bezeichnung	Qty	Description
VR10F	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR11A	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR11B	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR11C	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR11D	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR11E	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR11F	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
	813588	PCBAR PM 1000-2	1	pcb assy 81358
CN002	344975	MESSERLST. 10POL	1	connector male 10-pin
CN003	349117	MESSERLST. 14POL	1	connector male 14-pin
C001A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C001B	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C001C	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C001D	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C002A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C002B	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C002C	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C002D	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C003A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C003B	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C003C	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C003D	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C004A	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C004B	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C004C	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C004D	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C005A	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C005B	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C005C	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C005D	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C006A	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C006B	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C006C	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C006D	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C007A	362361	KO-EL 470.00MF 6.3V	1	cap electrolytic 470uF/6.3V
C007B	362361	KO-EL 470.00MF 6.3V	1	cap electrolytic 470uF/6.3V
C007C	362361	KO-EL 470.00MF 6.3V	1	cap electrolytic 470uF/6.3V
C007D	362361	KO-EL 470.00MF 6.3V	1	cap electrolytic 470uF/6.3V
C008A	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C008B	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C008C	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C008D	357452	KO-KER 330.0PF 100V 10%	1	cap ceramic 330pF
C009A	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C009B	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C009C	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C009D	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C010A	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C010B	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C010C	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C010D	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C020A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C020B	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C020C	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C020D	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C021A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C021B	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C021C	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C021D	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C022A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C022B	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C022C	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C022D	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C023A	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C023B	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C023C	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C023D	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C024A	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C024B	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C024C	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C024D	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C025A	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C025B	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C025C	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C025D	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C026A	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C026B	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C026C	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C026D	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C027A	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C027B	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C027C	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C027D	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C028A	362361	KO-EL 470.00MF 6.3V	1	cap electrolytic 470uF/6.3V
C028B	362361	KO-EL 470.00MF 6.3V	1	cap electrolytic 470uF/6.3V
C028C	362361	KO-EL 470.00MF 6.3V	1	cap electrolytic 470uF/6.3V
C028D	362361	KO-EL 470.00MF 6.3V	1	cap electrolytic 470uF/6.3V
C029A	362361	KO-EL 470.00MF 6.3V	1	cap electrolytic 470uF/6.3V
C029B	362361	KO-EL 470.00MF 6.3V	1	cap electrolytic 470uF/6.3V
C029C	362361	KO-EL 470.00MF 6.3V	1	cap electrolytic 470uF/6.3V
C029D	362361	KO-EL 470.00MF 6.3V	1	cap electrolytic 470uF/6.3V
C030A	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C030B	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C030C	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C030D	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C031A	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C031B	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C031C	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C031D	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C032A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C032B	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C032C	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C032D	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V

	112960	POWERMATE 1600-2 230V		
Pos. Nr.	Best. Nr.		Menge	
Ref. No.	Part No.	Bezeichnung	Qty	Description
C033A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C033B	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C033C	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C033D	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C034A	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C034B	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C034C	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C034D	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C035A	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C035B	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C035C	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C035D	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C036A	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C036B	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C036C	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C036D	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C037A	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C037B	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C037C	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C037D	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C038A	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C038B	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C038C	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C038D	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C039A	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C039B	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C039C	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C039D	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C040A	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C040B	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C040C	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C040D	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C041A	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C041B	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C041C	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C041D	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C042A	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C042B	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C042C	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C042D	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C043A	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C043B	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C043C	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C043D	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C044A	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C044B	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C044C	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C044D	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C045A	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C045B	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C045C	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C045D	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF

	112960	POWERMATE 1600-2 230V				
Pos. Nr.	Best. Nr.				Menge	
Ref. No.	Part No.	Bezeichnung			Qty	Description
C046A	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C046B	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C046C	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C046D	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C047A	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C047B	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C047C	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C047D	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C048A	301519	KO-KER	10.0PF	500V 10%	1	cap ceramic 10pF
C048B	301519	KO-KER	10.0PF	500V 10%	1	cap ceramic 10pF
C048C	301519	KO-KER	10.0PF	500V 10%	1	cap ceramic 10pF
C048D	301519	KO-KER	10.0PF	500V 10%	1	cap ceramic 10pF
C049A	301519	KO-KER	10.0PF	500V 10%	1	cap ceramic 10pF
C049B	301519	KO-KER	10.0PF	500V 10%	1	cap ceramic 10pF
C049C	301519	KO-KER	10.0PF	500V 10%	1	cap ceramic 10pF
C049D	301519	KO-KER	10.0PF	500V 10%	1	cap ceramic 10pF
C050A	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C050B	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C050C	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C050D	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C051A	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C051B	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C051C	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C051D	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C052A	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C052B	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C052C	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C052D	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C053A	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C053B	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C053C	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C053D	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C054A	301530	KO-KER	100.0PF	500V 10%	1	cap ceramic 100pF
C054B	301530	KO-KER	100.0PF	500V 10%	1	cap ceramic 100pF
C054C	301530	KO-KER	100.0PF	500V 10%	1	cap ceramic 100pF
C054D	301530	KO-KER	100.0PF	500V 10%	1	cap ceramic 100pF
C055A	301530	KO-KER	100.0PF	500V 10%	1	cap ceramic 100pF
C055B	301530	KO-KER	100.0PF	500V 10%	1	cap ceramic 100pF
C055C	301530	KO-KER	100.0PF	500V 10%	1	cap ceramic 100pF
C055D	301530	KO-KER	100.0PF	500V 10%	1	cap ceramic 100pF
C056A	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C056B	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C056C	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C056D	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C057A	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C057B	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C057C	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C057D	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C058A	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C058B	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C058C	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C058D	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V

	112960	POWERMATE 1600-2 230V			
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description	
C059A	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C059B	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C059C	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C059D	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C082A	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C082B	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C082C	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C082D	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C090A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C090B	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C091A	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C091B	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C092A	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C092B	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C093A	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C093B	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C094A	356508	KO-KER 0.10MF 50V 20%	1	cap ceramic 100nF	
C094B	356508	KO-KER 0.10MF 50V 20%	1	cap ceramic 100nF	
C095A	356508	KO-KER 0.10MF 50V 20%	1	cap ceramic 100nF	
C095B	356508	KO-KER 0.10MF 50V 20%	1	cap ceramic 100nF	
C096A	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C096B	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C097A	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C097B	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C098A	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V	
C098B	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V	
D001A	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148	
D001B	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148	
D001C	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148	
D001D	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148	
D002A	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148	
D002B	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148	
D002C	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148	
D002D	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148	
D003A	357450	LED GE 3MM LY 3369-EH	1	LED yellow 3mm	
D004A	354003	LED RT 3MM LOW CURRENT	1	led red	
D004B	354003	LED RT 3MM LOW CURRENT	1	led red	
D004C	354003	LED RT 3MM LOW CURRENT	1	led red	
D004D	354003	LED RT 3MM LOW CURRENT	1	led red	
D005A	354005	LED GE 3MM LOW CURRENT	1	led yellow	
D005B	354005	LED GE 3MM LOW CURRENT	1	led yellow	
D005C	354005	LED GE 3MM LOW CURRENT	1	led yellow	
D005D	354005	LED GE 3MM LOW CURRENT	1	led yellow	
D006A	354004	LED GN 3MM LOW CURRENT	1	led green	
D006B	354004	LED GN 3MM LOW CURRENT	1	led green	
D006C	354004	LED GN 3MM LOW CURRENT	1	led green	
D006D	354004	LED GN 3MM LOW CURRENT	1	led green	
D007A	354003	LED RT 3MM LOW CURRENT	1	led red	
D007B	354003	LED RT 3MM LOW CURRENT	1	led red	
D007C	354003	LED RT 3MM LOW CURRENT	1	led red	
D007D	354003	LED RT 3MM LOW CURRENT	1	led red	
D075A	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85	

	112960	POWERMATE 1600-2 230V			
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung		Menge Qty	Description
D075B	301297	DIODE BAT 85	SCHOTTKY	1	diode BAT 85
D075C	301297	DIODE BAT 85	SCHOTTKY	1	diode BAT 85
D075D	301297	DIODE BAT 85	SCHOTTKY	1	diode BAT 85
D077A	301297	DIODE BAT 85	SCHOTTKY	1	diode BAT 85
D077B	301297	DIODE BAT 85	SCHOTTKY	1	diode BAT 85
D077C	301297	DIODE BAT 85	SCHOTTKY	1	diode BAT 85
D077D	301297	DIODE BAT 85	SCHOTTKY	1	diode BAT 85
I001A	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I001B	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I002A	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I002B	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I003A	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I003B	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I004A	358661	IC NJM 2060 D		1	IC NJM 2060
I004B	358661	IC NJM 2060 D		1	IC NJM 2060
I005A	358661	IC NJM 2060 D		1	IC NJM 2060
I005B	358661	IC NJM 2060 D		1	IC NJM 2060
I006A	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I006B	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I007A	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I007B	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I008A	343502	IC LM 2901 N		1	IC LM 2901
I008B	343502	IC LM 2901 N		1	IC LM 2901
JS01A	354000	BUCHSE-FL. XLR 3POL	SW	1	connector XLR female 3-pole
JS01B	354000	BUCHSE-FL. XLR 3POL	SW	1	connector XLR female 3-pole
JS01C	354000	BUCHSE-FL. XLR 3POL	SW	1	connector XLR female 3-pole
JS01D	354000	BUCHSE-FL. XLR 3POL	SW	1	connector XLR female 3-pole
JS02A	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS02B	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS02C	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS02D	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS03A	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS03B	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS03C	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
JS03D	354001	BUCHSE-KOAXIAL-STEREO		1	phone jack stereo
Q001A	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q001B	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q001C	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q001D	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q002A	301184	TRANS BC 550 C		1	transistor BC 550 B
Q002B	301184	TRANS BC 550 C		1	transistor BC 550 B
Q002C	301184	TRANS BC 550 C		1	transistor BC 550 B
Q002D	301184	TRANS BC 550 C		1	transistor BC 550 B
Q003A	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q003B	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q003C	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q003D	343536	TRANS 2SA 1084 E	TO 92	1	transistor 2SA 1084 E
Q004A	301184	TRANS BC 550 C		1	transistor BC 550 B
Q004B	301184	TRANS BC 550 C		1	transistor BC 550 B
Q004C	301184	TRANS BC 550 C		1	transistor BC 550 B
Q004D	301184	TRANS BC 550 C		1	transistor BC 550 B
R100A	340299	WI-SI 2.20 OHM 0.30W 5%		1	safety resistor 2.20 Ohm

	112960	POWERMATE 1600-2 230V		
Pos. Nr.	Best. Nr.		Menge	
Ref. No.	Part No.	Bezeichnung	Qty	Description
R100B	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R101A	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R101B	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
S0001	354006	SCHALTER-RAST 2XUM	1	switch dpdt
S001A	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S001B	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S001C	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S001D	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S002A	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S002B	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S002C	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S002D	357446	SCHALTER-TAST 2XUM	1	switch dpdt
VR01A	352323	P-DREH 5KOHM LOG-	1	pot 5k neg log
VR01B	352323	P-DREH 5KOHM LOG-	1	pot 5k neg log
VR01C	352323	P-DREH 5KOHM LOG-	1	pot 5k neg log
VR01D	352323	P-DREH 5KOHM LOG-	1	pot 5k neg log
VR02A	352330	P-DREH 2X 5KOHM LOG+	1	pot 2x5k log
VR02B	352330	P-DREH 2X 5KOHM LOG+	1	pot 2x5k log
VR02C	352330	P-DREH 2X 5KOHM LOG+	1	pot 2x5k log
VR02D	352330	P-DREH 2X 5KOHM LOG+	1	pot 2x5k log
VR03A	352331	P-DREH 2X 50KOHM LIN	1	pot 2x50k B
VR03B	352331	P-DREH 2X 50KOHM LIN	1	pot 2x50k B
VR03C	352331	P-DREH 2X 50KOHM LIN	1	pot 2x50k B
VR03D	352331	P-DREH 2X 50KOHM LIN	1	pot 2x50k B
VR04A	352331	P-DREH 2X 50KOHM LIN	1	pot 2x50k B
VR04B	352331	P-DREH 2X 50KOHM LIN	1	pot 2x50k B
VR04C	352331	P-DREH 2X 50KOHM LIN	1	pot 2x50k B
VR04D	352331	P-DREH 2X 50KOHM LIN	1	pot 2x50k B
VR05A	352331	P-DREH 2X 50KOHM LIN	1	pot 2x50k B
VR05B	352331	P-DREH 2X 50KOHM LIN	1	pot 2x50k B
VR05C	352331	P-DREH 2X 50KOHM LIN	1	pot 2x50k B
VR05D	352331	P-DREH 2X 50KOHM LIN	1	pot 2x50k B
VR06A	362357	P-SHIB 2X 20KOHM LOG+	1	fader 2x20k log
VR06B	362357	P-SHIB 2X 20KOHM LOG+	1	fader 2x20k log
VR06C	362357	P-SHIB 2X 20KOHM LOG+	1	fader 2x20k log
VR06D	362357	P-SHIB 2X 20KOHM LOG+	1	fader 2x20k log
VR07A	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k
VR07B	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k
VR07C	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k
VR07D	352327	P-DREH 2X 10KOHM LOG+/LOG-	1	pot 2x10k
VR08A	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR08B	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR08C	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR08D	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR09A	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR09B	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR09C	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR09D	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR10A	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR10B	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR10C	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR10D	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
VR11A	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR11B	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR11C	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR11D	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
	822348	PCBDAR PM 1000-2	1	pcb assy 82234
CN001	345489	MESSERLST. 6POL	1	connector male 6-pin
CN002	349105	MESSERLST. 20POL	1	connector male 20-pin
CN003	348488	FEDERLEISTE 6POL 2.54MM	1	connector female 6-pole
CN004	348488	FEDERLEISTE 6POL 2.54MM	1	connector female 6-pole
CN005	348488	FEDERLEISTE 6POL 2.54MM	1	connector female 6-pole
CN006	349117	MESSERLST. 14POL	1	connector male 14-pin
CN007	344975	MESSERLST. 10POL	1	connector male 10-pin
C0001	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0002	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0003	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0004	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0005	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0006	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0007	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0008	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0009	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0010	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C0011	346975	KO-FOL 3300.000PF 100V 5%	1	cap mylar 3.3nF
C0012	342936	KO-FOL 0.150MF 63V 5%	1	cap mylar 150nF
C0013	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0014	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0015	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0016	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0017	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF
C0018	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0019	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0020	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0021	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0022	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0023	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0024	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0025	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0026	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0027	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0028	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0029	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0030	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0031	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0032	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0033	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0034	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0035	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0036	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0037	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0038	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V

	112960	POWERMATE 1600-2 230V			
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description	
C0039	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C0040	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C0041	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C0042	327366	KO-EL 4.700MF 50V BIP	1	cap bip electr. 4.7uF/50V	
C0043	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C0044	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C0045	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C0046	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C0047	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C0048	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C0049	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C0050	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C0051	356508	KO-KER 0.10MF 50V 20%	1	cap ceramic 100nF	
C0210	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C0211	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C0212	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF	
C0213	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF	
C0214	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF	
C0215	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF	
C0216	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF	
C0217	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF	
C0218	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C0219	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C0220	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF	
C0221	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF	
C0222	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF	
C0223	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF	
C0224	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C0225	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C0226	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF	
C0227	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF	
C0228	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF	
C0229	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF	
C0231	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF	
C0232	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C0233	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF	
C0234	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V	
C0235	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF	
C0236	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF	
C0238	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C0301	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C0302	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C0303	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C0304	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C0305	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C0306	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C0307	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C0308	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF	
C0309	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C0310	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF	
C0311	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V	
C0312	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF	

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0313	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0314	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0315	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0316	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0317	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0318	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0319	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0320	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0321	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0322	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0323	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0324	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0326	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0327	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0328	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0329	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0330	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0331	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0332	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0333	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0334	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0335	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0336	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0337	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0338	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0339	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0340	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0341	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0342	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0343	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0345	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0346	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0347	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0348	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0349	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0350	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0351	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0352	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0353	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0354	344189	KO-FOL 2200.000PF 100V 5%	1	cap mylar 2.2nF
C0355	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0357	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0359	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0361	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0362	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0363	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0364	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0365	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0400	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0401	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0402	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0403	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0406	346975	KO-FOL 3300.000PF 100V 5%	1	cap mylar 3.3nF
C0407	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0408	342936	KO-FOL 0.150MF 63V 5%	1	cap mylar 150nF
C0409	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0410	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0411	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF
C0412	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0413	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0414	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0415	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0416	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0417	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0418	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0419	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0420	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0421	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0422	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0423	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0424	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0425	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0426	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0427	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0428	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0429	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0500	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0501	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0502	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0503	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0504	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0505	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0506	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0507	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0508	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0509	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0510	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0511	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0512	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0513	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0514	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0515	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0516	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0517	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0518	327393	KO-FOL 4700.000PF 63V 5%	1	cap mylar 4700pF
C0519	327393	KO-FOL 4700.000PF 63V 5%	1	cap mylar 4700pF
C0520	327392	KO-FOL 3900.000PF 63V 5%	1	cap mylar 3900pF
C0521	327392	KO-FOL 3900.000PF 63V 5%	1	cap mylar 3900pF
C0522	300050	KO-FOL 330.000PF 100V 5%	1	cap mylar 330pF
C0523	300050	KO-FOL 330.000PF 100V 5%	1	cap mylar 330pF
C0524	344104	KO-FOL 0.018MF 100V 5%	1	cap mylar 18nF
C0525	344104	KO-FOL 0.018MF 100V 5%	1	cap mylar 18nF
C0528	300049	KO-FOL 680.000PF 100V 5%	1	cap mylar 680pF
C0529	300049	KO-FOL 680.000PF 100V 5%	1	cap mylar 680pF

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0530	337237	KO-FOL 0.047MF 100V 5%	1	cap mylar 47nF
C0531	337237	KO-FOL 0.047MF 100V 5%	1	cap mylar 47nF
C0534	327391	KO-FOL 1500.000PF 100V 5%	1	cap mylar 1500pF
C0535	327391	KO-FOL 1500.000PF 100V 5%	1	cap mylar 1500pF
C0536	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C0537	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C0540	327393	KO-FOL 4700.000PF 63V 5%	1	cap mylar 4700pF
C0541	327393	KO-FOL 4700.000PF 63V 5%	1	cap mylar 4700pF
C0542	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0543	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0544	342933	KO-FOL 0.022MF 100V 5%	1	cap mylar 22nF
C0545	342933	KO-FOL 0.022MF 100V 5%	1	cap mylar 22nF
C0546	337181	KO-FOL 0.010MF 100V 5%	1	cap mylar 10nF
C0547	337181	KO-FOL 0.010MF 100V 5%	1	cap mylar 10nF
C0548	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0549	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0550	340244	KO-FOL 0.330MF 63V 5%	1	cap mylar 330nF
C0551	340244	KO-FOL 0.330MF 63V 5%	1	cap mylar 330nF
C0552	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C0553	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C0554	342937	KO-FOL 1.000MF 63V 5%	1	cap mylar 1uF
C0555	342937	KO-FOL 1.000MF 63V 5%	1	cap mylar 1uF
C0556	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0557	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0560	344109	KO-FOL 0.056MF 63V 5%	1	cap mylar 56nF
C0561	344109	KO-FOL 0.056MF 63V 5%	1	cap mylar 56nF
C0562	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0563	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0564	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0565	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0566	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0567	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0568	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0569	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0570	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0571	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0572	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0573	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0574	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0575	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0576	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0577	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0578	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0579	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0582	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0583	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
D0001	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0002	329511	DIODZ BZX 55C 2V4 0.50W	1	diode zener 2V4
D0003	354004	LED GN 3MM LOW CURRENT	1	led green
D0004	354004	LED GN 3MM LOW CURRENT	1	led green
D0005	354004	LED GN 3MM LOW CURRENT	1	led green
D0006	354004	LED GN 3MM LOW CURRENT	1	led green

	112960	POWERMATE 1600-2 230V				
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung			Menge Qty	Description
D0007	354004	LED GN	3MM	LOW CURRENT	1	led green
D0008	354004	LED GN	3MM	LOW CURRENT	1	led green
D0009	354004	LED GN	3MM	LOW CURRENT	1	led green
D0010	354004	LED GN	3MM	LOW CURRENT	1	led green
D0011	354004	LED GN	3MM	LOW CURRENT	1	led green
D0012	354003	LED RT	3MM	LOW CURRENT	1	led red
D0013	354004	LED GN	3MM	LOW CURRENT	1	led green
D0014	354004	LED GN	3MM	LOW CURRENT	1	led green
D0015	354004	LED GN	3MM	LOW CURRENT	1	led green
D0016	354004	LED GN	3MM	LOW CURRENT	1	led green
D0017	354004	LED GN	3MM	LOW CURRENT	1	led green
D0018	354004	LED GN	3MM	LOW CURRENT	1	led green
D0019	354004	LED GN	3MM	LOW CURRENT	1	led green
D0020	354004	LED GN	3MM	LOW CURRENT	1	led green
D0021	354004	LED GN	3MM	LOW CURRENT	1	led green
D0022	354003	LED RT	3MM	LOW CURRENT	1	led red
D0023	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D0024	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D0025	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D0026	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D0027	354003	LED RT	3MM	LOW CURRENT	1	led red
D0028	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D0029	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D0030	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D0031	354004	LED GN	3MM	LOW CURRENT	1	led green
D0032	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D0033	354003	LED RT	3MM	LOW CURRENT	1	led red
D0034	354003	LED RT	3MM	LOW CURRENT	1	led red
D0035	329511	DIODZ BZX 55C 2V4 0.50W			1	diode zener 2V4
D0036	354004	LED GN	3MM	LOW CURRENT	1	led green
D0037	354004	LED GN	3MM	LOW CURRENT	1	led green
D0039	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D0040	354003	LED RT	3MM	LOW CURRENT	1	led red
D0041	354003	LED RT	3MM	LOW CURRENT	1	led red
D0042	354004	LED GN	3MM	LOW CURRENT	1	led green
D0043	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D0044	354004	LED GN	3MM	LOW CURRENT	1	led green
D0045	354003	LED RT	3MM	LOW CURRENT	1	led red
D0046	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D0047	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D0048	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D0049	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D0050	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D0051	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D0052	354004	LED GN	3MM	LOW CURRENT	1	led green
D0053	354004	LED GN	3MM	LOW CURRENT	1	led green
D0054	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D0055	354005	LED GE	3MM	LOW CURRENT	1	led yellow
D0056	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
E0001	357448	RELAIS			1	relay
E0002	357448	RELAIS			1	relay
I0001	331340	IC TL 072 CP	2FACH OP		1	IC TL 072 CP

	112960	POWERMATE 1600-2 230V		
Pos. Nr.	Best. Nr.		Menge	
Ref. No.	Part No.	Bezeichnung	Qty	Description
I0002	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0003	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0004	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0005	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0006	346343	IC SPNG.REG. MC 78L05 ACP	1	IC MC 78 L 05 ACP
I0009	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0010	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0011	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0012	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0013	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0014	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0015	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0016	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0017	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0018	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0019	344864	IC NJM 4556 AD 2-FACH OP	1	IC NJM 4556 D
I0020	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0021	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0023	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0025	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0026	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0027	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0028	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0030	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0031	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0032	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0033	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0034	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0035	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0037	343502	IC LM 2901 N	1	IC LM 2901
I0038	343502	IC LM 2901 N	1	IC LM 2901
I0039	343502	IC LM 2901 N	1	IC LM 2901
I0040	343502	IC LM 2901 N	1	IC LM 2901
I0041	343502	IC LM 2901 N	1	IC LM 2901
I0042	343502	IC LM 2901 N	1	IC LM 2901
I0043	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0044	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
JS001	354000	BUCHSE-FL. XLR 3POL SW	1	connector XLR female 3-pole
JS002	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS003	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS005	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS006	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS007	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS008	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS009	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS010	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS011	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS012	354002	BUCHSE-CINCH 4X CINCH	1	connector cinch
JS013	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS014	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS016	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS017	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo

	112960	POWERMATE 1600-2 230V		
Pos. Nr.	Best. Nr.		Menge	
Ref. No.	Part No.	Bezeichnung	Qty	Description
JS018	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS020	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS021	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS022	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
JS023	354001	BUCHSE-KOAXIAL-STEREO	1	phone jack stereo
Q0001	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0002	307430	TRANS BC 327-25 TO 92	1	transistor BC 327-25
Q0003	307430	TRANS BC 327-25 TO 92	1	transistor BC 327-25
Q0006	301184	TRANS BC 550 C	1	transistor BC 550 B
Q0007	301184	TRANS BC 550 C	1	transistor BC 550 B
Q0008	330264	TRANS J 111	1	transistor J 111 A
Q0009	330264	TRANS J 111	1	transistor J 111 A
Q0010	301184	TRANS BC 550 C	1	transistor BC 550 B
Q0011	301184	TRANS BC 550 C	1	transistor BC 550 B
Q0012	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0013	301184	TRANS BC 550 C	1	transistor BC 550 B
Q0014	301184	TRANS BC 550 C	1	transistor BC 550 B
Q0016	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0017	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0018	330264	TRANS J 111	1	transistor J 111 A
Q0019	330264	TRANS J 111	1	transistor J 111 A
R0068	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0069	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0301	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0302	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0369	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0370	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0437	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0438	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0552	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0553	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0575	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0577	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
S0001	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0002	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0003	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0004	357447	SCHALTER-TAST 4XUM	1	switch 4pdt
S0005	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0006	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0007	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0008	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0009	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0010	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0011	357445	SCHALTER-TAST 2XUM	1	switch dpdt
S0012	357445	SCHALTER-TAST 2XUM	1	switch dpdt
S0013	357445	SCHALTER-TAST 2XUM	1	switch dpdt
S0014	357445	SCHALTER-TAST 2XUM	1	switch dpdt
S0015	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0016	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0017	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0018	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0019	357446	SCHALTER-TAST 2XUM	1	switch dpdt

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
S0020	357446	SCHALTER-TAST 2XUM	1	switch dpdt
S0021	357446	SCHALTER-TAST 2XUM	1	switch dpdt
VR001	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR002	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR003	354288	P-DREH 2X100KOHM LOG-	1	pot 2x100k C
VR004	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR011	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR012	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR013	362357	P-SHIB 2X 20KOHM LOG+	1	fader 2x20k log
VR014	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR015	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR016	362357	P-SHIB 2X 20KOHM LOG+	1	fader 2x20k log
VR017	354288	P-DREH 2X100KOHM LOG-	1	pot 2x100k C
VR018	362356	P-SHIB 10KOHM LOG+	1	fader 10k log
VR019	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
VR020	352328	P-DREH 20KOHM LOG+	1	pot 20k log
VR022	362417	P-SHIB 10KOHM SELEKT.AUS	1	fader 10k selected
VR023	362417	P-SHIB 10KOHM SELEKT.AUS	1	fader 10k selected
VR024	362359	P-SHIB 10KOHM LIN	1	fader 10k lin
VR025	362359	P-SHIB 10KOHM LIN	1	fader 10k lin
VR026	362359	P-SHIB 10KOHM LIN	1	fader 10k lin
VR027	362359	P-SHIB 10KOHM LIN	1	fader 10k lin
VR028	362359	P-SHIB 10KOHM LIN	1	fader 10k lin
VR029	362359	P-SHIB 10KOHM LIN	1	fader 10k lin
VR030	362359	P-SHIB 10KOHM LIN	1	fader 10k lin
VR031	362359	P-SHIB 10KOHM LIN	1	fader 10k lin
VR032	362359	P-SHIB 10KOHM LIN	1	fader 10k lin
VR033	362359	P-SHIB 10KOHM LIN	1	fader 10k lin
VR034	362359	P-SHIB 10KOHM LIN	1	fader 10k lin
VR035	362359	P-SHIB 10KOHM LIN	1	fader 10k lin
VR036	362359	P-SHIB 10KOHM LIN	1	fader 10k lin
VR037	362359	P-SHIB 10KOHM LIN	1	fader 10k lin
VR038	362356	P-SHIB 10KOHM LOG+	1	fader 10k log
VR039	362355	P-DREH 2X 20KOHM LOG+	1	pot 2x20k log
	842298	PCBAR PM 1000-2	1	pcb assy 84229
CN-FX	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNAC1	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CNAC2	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CNGN1	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CNGN2	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNS01	337395	STIFTLEISTE 6POL	1	connector male 6-pin
CNS02	337395	STIFTLEISTE 6POL	1	connector male 6-pin
CNS03	327781	STIFTLEISTE 8POL	1	connector male 8-pin
CNS04	327781	STIFTLEISTE 8POL	1	connector male 8-pin
CN001	345489	MESSERLST. 6POL	1	connector male 6-pin
CN002	349105	MESSERLST. 20POL	1	connector male 20-pin
CN003	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN005	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN006	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN011	329022	FL.STECKER 6.3/0.8	1	connector 6.3mm faston

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
CN012	329022	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN014	329022	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN015	329022	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN016	341937	MESSERLST. 4POL	1	connector male 4-pin
CN019	329022	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN16X	341937	MESSERLST. 4POL	1	connector male 4-pin
C0001	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0002	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0003	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0004	362471	KO-EL 12000.000MF 63V	1	cap electr. 12000uF/63V
C0005	362471	KO-EL 12000.000MF 63V	1	cap electr. 12000uF/63V
C0006	362471	KO-EL 12000.000MF 63V	1	cap electr. 12000uF/63V
C0007	362471	KO-EL 12000.000MF 63V	1	cap electr. 12000uF/63V
C0008	362471	KO-EL 12000.000MF 63V	1	cap electr. 12000uF/63V
C0009	362471	KO-EL 12000.000MF 63V	1	cap electr. 12000uF/63V
C0010	362471	KO-EL 12000.000MF 63V	1	cap electr. 12000uF/63V
C0011	362471	KO-EL 12000.000MF 63V	1	cap electr. 12000uF/63V
C0012	342937	KO-FOL 1.000MF 63V 5%	1	cap mylar 1uF
C0013	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0014	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0015	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0017	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0018	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0019	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0020	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0021	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0022	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0023	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0024	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0025	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0026	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0027	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0028	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0029	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0032	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0033	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0034	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0035	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0036	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0037	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0038	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0039	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0040	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0041	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0042	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0043	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0044	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0045	344105	KO-FOL 0.027MF 100V 5%	1	cap mylar 27nF
C0046	342937	KO-FOL 1.000MF 63V 5%	1	cap mylar 1uF
C0047	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0048	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0049	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0050	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0051	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0052	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0053	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0054	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0055	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0056	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0057	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0058	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0059	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0060	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0063	342936	KO-FOL 0.150MF 63V 5%	1	cap mylar 150nF
C0064	342936	KO-FOL 0.150MF 63V 5%	1	cap mylar 150nF
C0066	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0067	341920	KO-EL 470.000MF 63V	1	cap electrolytic 470uF/63V
C0068	342361	KO-KER 47.0PF K 100V 2%	1	cap ceramic 47pF
C0069	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0070	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0071	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0072	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0073	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0074	335935	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0075	343534	KO-EL 1000.000MF 16V	1	cap electrolytic 1000uF/16V
C0076	343534	KO-EL 1000.000MF 16V	1	cap electrolytic 1000uF/16V
C0077	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0078	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0079	362475	KO-EL 100.000MF 63V	1	cap electrolytic 100uF/63V
C0080	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0081	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0082	344105	KO-FOL 0.027MF 100V 5%	1	cap mylar 27nF
C0083	362475	KO-EL 100.000MF 63V	1	cap electrolytic 100uF/63V
C0084	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0085	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0086	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0087	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0088	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0089	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0090	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0091	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0092	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0103	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0104	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0105	342936	KO-FOL 0.150MF 63V 5%	1	cap mylar 150nF
C0115	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0117	301522	KO-KER 22.0PF 500V 10%	1	cap ceramic 22pF
C0118	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0119	327391	KO-FOL 1500.000PF 100V 5%	1	cap mylar 1500pF
C0120	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0121	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0122	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0123	340244	KO-FOL 0.330MF 63V 5%	1	cap mylar 330nF
C0124	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0125	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0126	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0127	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0128	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0129	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0131	358639	KO-EL 220.000MF 16V	1	cap electrolytic 220uF/16V
C0132	348846	KO-KER 680.0PF 500V 5%	1	cap ceramic 680pF
C0133	348846	KO-KER 680.0PF 500V 5%	1	cap ceramic 680pF
C0136	304986	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0137	356605	KO-FOL 0.100MF 250V 5%	1	cap mylar 100nF
C0139	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0140	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0141	301474	KO-EL 22.000MF 16V BIP	1	cap bip electr. 22uF/16V
C0142	362036	KO-FOL 0.010MF 250V 5%	1	cap mylar 10nF
C0143	362036	KO-FOL 0.010MF 250V 5%	1	cap mylar 10nF
C0144	348846	KO-KER 680.0PF 500V 5%	1	cap ceramic 680pF
C0146	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0147	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0148	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0149	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0150	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0151	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0152	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0153	343533	KO-EL 220.000MF 25V	1	cap electrolytic 220uF/25V
C0154	343533	KO-EL 220.000MF 25V	1	cap electrolytic 220uF/25V
C0155	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0156	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0159	342937	KO-FOL 1.000MF 63V 5%	1	cap mylar 1uF
C0303	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0304	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0305	342936	KO-FOL 0.150MF 63V 5%	1	cap mylar 150nF
C0315	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0317	301522	KO-KER 22.0PF 500V 10%	1	cap ceramic 22pF
C0318	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0319	327391	KO-FOL 1500.000PF 100V 5%	1	cap mylar 1500pF
C0320	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0321	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0322	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0323	340244	KO-FOL 0.330MF 63V 5%	1	cap mylar 330nF
C0324	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0325	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0326	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0327	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0328	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0329	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0331	358639	KO-EL 220.000MF 16V	1	cap electrolytic 220uF/16V
C0332	348846	KO-KER 680.0PF 500V 5%	1	cap ceramic 680pF
C0333	348846	KO-KER 680.0PF 500V 5%	1	cap ceramic 680pF
C0336	304986	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0337	356605	KO-FOL 0.100MF 250V 5%	1	cap mylar 100nF
C0339	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0340	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0341	301474	KO-EL 22.000MF 16V BIP	1	cap bip electr. 22uF/16V
C0342	362036	KO-FOL 0.010MF 250V 5%	1	cap mylar 10nF
C0343	362036	KO-FOL 0.010MF 250V 5%	1	cap mylar 10nF
C0344	348846	KO-KER 680.0PF 500V 5%	1	cap ceramic 680pF
C0346	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0347	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0348	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0349	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0350	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0351	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0352	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0353	343533	KO-EL 220.000MF 25V	1	cap electrolytic 220uF/25V
C0354	343533	KO-EL 220.000MF 25V	1	cap electrolytic 220uF/25V
C0355	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0356	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0359	342937	KO-FOL 1.000MF 63V 5%	1	cap mylar 1uF
D0001	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0002	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0003	359369	DIODE 1N 5404 BEARB.AUS	1	diode 1N 5404
D0004	359369	DIODE 1N 5404 BEARB.AUS	1	diode 1N 5404
D0005	359369	DIODE 1N 5404 BEARB.AUS	1	diode 1N 5404
D0006	359369	DIODE 1N 5404 BEARB.AUS	1	diode 1N 5404
D0007	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0008	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0009	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0010	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0011	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0012	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0013	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0014	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0015	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0016	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0017	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0018	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0019	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0020	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0021	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0022	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0023	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0024	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0025	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0026	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0027	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0028	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0029	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0030	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0033	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0034	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0035	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0036	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0100	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0101	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
D0102	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0103	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0104	329511	DIODZ BZX 55C 2V4 0.50W	1	diode zener 2V4
D0107	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0108	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0109	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0110	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0111	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0112	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0113	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0114	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0115	359369	DIODE 1N 5404 BEARB.AUS	1	diode 1N 5404
D0116	359369	DIODE 1N 5404 BEARB.AUS	1	diode 1N 5404
D0117	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0118	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0119	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0120	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0121	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0122	362170	DIODE FFPF30U20STU ULTRAF.	1	diode FFPF30U20STU
D0123	362170	DIODE FFPF30U20STU ULTRAF.	1	diode FFPF30U20STU
D0124	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0125	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0126	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0127	305738	DIODZ BZX 55C 12V 0.50W	1	diode zener 12V
D0128	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0129	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0130	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0131	333733	DIODZ BZX 85C 12V 1.30W	1	diode zener 12V
D0134	301277	DIODZ BZX 55C 18V 0.50W	1	diode zener 18V
D0135	301277	DIODZ BZX 55C 18V 0.50W	1	diode zener 18V
D0136	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0137	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0300	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0301	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0302	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0303	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0304	329511	DIODZ BZX 55C 2V4 0.50W	1	diode zener 2V4
D0307	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0308	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0309	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0310	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0311	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0312	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0313	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0314	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0315	359369	DIODE 1N 5404 BEARB.AUS	1	diode 1N 5404
D0316	359369	DIODE 1N 5404 BEARB.AUS	1	diode 1N 5404
D0317	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0318	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0319	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0320	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0321	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148

	112960	POWERMATE 1600-2 230V		
Pos. Nr.	Best. Nr.		Menge	
Ref. No.	Part No.	Bezeichnung	Qty	Description
D0322	362170	DIODE FFPF30U20STU ULTRAF.	1	diode FFPF30U20STU
D0323	362170	DIODE FFPF30U20STU ULTRAF.	1	diode FFPF30U20STU
D0324	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0325	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0326	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0327	305738	DIODZ BZX 55C 12V 0.50W	1	diode zener 12V
D0328	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0329	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0330	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0331	333733	DIODZ BZX 85C 12V 1.30W	1	diode zener 12V
D0334	301277	DIODZ BZX 55C 18V 0.50W	1	diode zener 18V
D0335	301277	DIODZ BZX 55C 18V 0.50W	1	diode zener 18V
D0336	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0337	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
E0001	356594	RELAIS 793-P-1A-S-TV10	1	relay 24V / spst
E0100	354859	RELAIS 793-P-1C-S 24VDC	1	relay 24V
E0300	354859	RELAIS 793-P-1C-S 24VDC	1	relay 24V
F0001	302565	SICHER T 10.000 A/250V	1	fuse 10A slow blow
F0002	340559	SICHER T 4.000 A/250V	1	fuse 4A/250V slow blow
F0003	340559	SICHER T 4.000 A/250V	1	fuse 4A/250V slow blow
H0100	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0103	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0300	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0303	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
I0001	354199	IC SPNG.REGL. LM 317 T	1	IC LM 317 voltage regulator
I0002	354929	IC SPNG.REGL. LM 337 T	1	IC LM 337 voltage regulator
I0003	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0004	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0005	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0006	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0007	332985	IC TL 074 CN	1	IC TL 074 CN
I0008	354929	IC SPNG.REGL. LM 337 T	1	IC LM 337 voltage regulator
I0100	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0101	307421	IC CA 3080 E OTA	1	IC CA 3080 E
I0102	354919	IC OP 97 FP	1	IC OP 97
I0103	332985	IC TL 074 CN	1	IC TL 074 CN
I0104	330767	IC LM 311 P 1-F.VCOMP	1	IC LM 311
I0105	330767	IC LM 311 P 1-F.VCOMP	1	IC LM 311
I0300	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0301	307421	IC CA 3080 E OTA	1	IC CA 3080 E
I0302	354919	IC OP 97 FP	1	IC OP 97
I0303	332985	IC TL 074 CN	1	IC TL 074 CN
I0304	330767	IC LM 311 P 1-F.VCOMP	1	IC LM 311
I0305	330767	IC LM 311 P 1-F.VCOMP	1	IC LM 311
I0800	309719	IC SPNG.REGL. LM 7805 CT	1	IC MC 7805 C
JS001	338835	STECKER-KALTGERÄTE	1	connector male mains
L0100	348592	FILTERSP. 2.50UH/0.004OHM	1	coil 2.5uH
L0300	348592	FILTERSP. 2.50UH/0.004OHM	1	coil 2.5uH
Q0001	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0002	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0003	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0004	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
Q0005	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0006	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0007	348591	TRANS BC 618 DARL. TO 92	1	transistor BC 618
Q0008	301184	TRANS BC 550 C	1	transistor BC 550 B
Q0009	301184	TRANS BC 550 C	1	transistor BC 550 B
Q0010	301184	TRANS BC 550 C	1	transistor BC 550 B
Q0011	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25
Q0012	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25
Q0013	304592	TRANS BD 246 C	1	transistor BD 246 C
Q0014	304591	TRANS BD 245 C	1	transistor BD 245 C
Q0015	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25
Q0016	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0017	304576	TRANS BD 241 C	1	transistor BD 241 C
Q0021	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25
Q0101	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0102	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0103	330264	TRANS J 111	1	transistor J 111 A
Q0104	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0105	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0106	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0107	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0108	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0109	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0110	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0111	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0112	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0113	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0114	338869	TRANS MJE 350	1	transistor MJE 350
Q0115	338868	TRANS MJE 340	1	transistor MJE 340
Q0116	348409	TRANS 2SC 4793	1	transistor 2SC 4793
Q0117	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0118	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0119	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0120	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0121	359496	TRANS MJW 21196 TO 247	1	transistor MJW 21196
Q0122	359495	TRANS MJW 21195 TO 247	1	transistor MJW 21195
Q0123	359496	TRANS MJW 21196 TO 247	1	transistor MJW 21196
Q0124	359495	TRANS MJW 21195 TO 247	1	transistor MJW 21195
Q0125	359496	TRANS MJW 21196 TO 247	1	transistor MJW 21196
Q0126	359495	TRANS MJW 21195 TO 247	1	transistor MJW 21195
Q0127	359496	TRANS MJW 21196 TO 247	1	transistor MJW 21196
Q0128	359495	TRANS MJW 21195 TO 247	1	transistor MJW 21195
Q0129	359496	TRANS MJW 21196 TO 247	1	transistor MJW 21196
Q0130	359495	TRANS MJW 21195 TO 247	1	transistor MJW 21195
Q0135	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0136	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0137	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0138	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0139	307911	TRANS BF 393	1	transistor BF 391
Q0140	307911	TRANS BF 393	1	transistor BF 391
Q0141	307912	TRANS BF 493 S TO 92	1	transistor BF 491
Q0142	307912	TRANS BF 493 S TO 92	1	transistor BF 491

	112960	POWERMATE 1600-2 230V			
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description	
Q0143	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0144	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0145	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0146	359423	TRANS HUF 75542 P3 N-CHAN	1	transistor HUF 75542	
Q0147	359423	TRANS HUF 75542 P3 N-CHAN	1	transistor HUF 75542	
Q0148	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0149	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0150	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0151	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0152	338868	TRANS MJE 340	1	transistor MJE 340	
Q0153	338869	TRANS MJE 350	1	transistor MJE 350	
Q0154	359442	TRANS MJE 15032	1	transistor MJE 15032	
Q0155	359443	TRANS MJE 15033	1	transistor MJE 15033	
Q0156	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0157	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0301	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0302	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0303	330264	TRANS J 111	1	transistor J 111 A	
Q0304	348422	TRANS MPSA 42	1	transistor MPSA 42	
Q0305	348422	TRANS MPSA 42	1	transistor MPSA 42	
Q0306	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0307	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0308	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0309	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0310	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0311	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0312	348423	TRANS MPSA 92	1	transistor MPSA 92	
Q0313	348423	TRANS MPSA 92	1	transistor MPSA 92	
Q0314	338869	TRANS MJE 350	1	transistor MJE 350	
Q0315	338868	TRANS MJE 340	1	transistor MJE 340	
Q0316	348409	TRANS 2SC 4793	1	transistor 2SC 4793	
Q0317	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0318	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0319	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0320	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0321	359496	TRANS MJW 21196 TO 247	1	transistor MJW 21196	
Q0322	359495	TRANS MJW 21195 TO 247	1	transistor MJW 21195	
Q0323	359496	TRANS MJW 21196 TO 247	1	transistor MJW 21196	
Q0324	359495	TRANS MJW 21195 TO 247	1	transistor MJW 21195	
Q0325	359496	TRANS MJW 21196 TO 247	1	transistor MJW 21196	
Q0326	359495	TRANS MJW 21195 TO 247	1	transistor MJW 21195	
Q0327	359496	TRANS MJW 21196 TO 247	1	transistor MJW 21196	
Q0328	359495	TRANS MJW 21195 TO 247	1	transistor MJW 21195	
Q0329	359496	TRANS MJW 21196 TO 247	1	transistor MJW 21196	
Q0330	359495	TRANS MJW 21195 TO 247	1	transistor MJW 21195	
Q0335	348423	TRANS MPSA 92	1	transistor MPSA 92	
Q0336	348422	TRANS MPSA 42	1	transistor MPSA 42	
Q0337	348423	TRANS MPSA 92	1	transistor MPSA 92	
Q0338	348422	TRANS MPSA 42	1	transistor MPSA 42	
Q0339	307911	TRANS BF 393	1	transistor BF 391	
Q0340	307911	TRANS BF 393	1	transistor BF 391	
Q0341	307912	TRANS BF 493 S TO 92	1	transistor BF 491	

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
Q0342	307912	TRANS BF 493 S TO 92	1	transistor BF 491
Q0343	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0344	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0345	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0346	359423	TRANS HUF 75542 P3 N-CHAN	1	transistor HUF 75542
Q0347	359423	TRANS HUF 75542 P3 N-CHAN	1	transistor HUF 75542
Q0348	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0349	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0350	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0351	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0352	338868	TRANS MJE 340	1	transistor MJE 340
Q0353	338869	TRANS MJE 350	1	transistor MJE 350
Q0354	359442	TRANS MJE 15032	1	transistor MJE 15032
Q0355	359443	TRANS MJE 15033	1	transistor MJE 15033
Q0356	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0357	348421	TRANS 2N 3906	1	transistor 2N 3906
R0001	348550	WI-SO NTC 10.00 OHM K	1	resistor ntc 10 Ohm
R0054	358977	WI-SO NTC 12.00 KOHM	1	resistor ntc 12k Ohm
R0055	358977	WI-SO NTC 12.00 KOHM	1	resistor ntc 12k Ohm
R0098	362479	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm/5watt
R0099	362479	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm/5watt
R0205	362479	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm/5watt
R0206	362479	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm/5watt
R0207	362479	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm/5watt
R0208	362479	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm/5watt
R0225	348593	WI-SO NTC 2.20 KOHM	1	safety component NTC
R0226	348593	WI-SO NTC 2.20 KOHM	1	safety component NTC
R0242	341713	WI-DR 4.70 OHM 4.00W 5%	1	resistor 4.70 Ohm 4watt
R0243	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt
R0284	332306	WI-SCH 3.30 KOHM 2.00W 5%	1	resistor 3.3k Ohm 2watt
R0285	332306	WI-SCH 3.30 KOHM 2.00W 5%	1	resistor 3.3k Ohm 2watt
R0303	302022	WI-SCH 10.00 OHM 2.00W 5%	1	resistor 10 Ohm 2watt
R0305	302022	WI-SCH 10.00 OHM 2.00W 5%	1	resistor 10 Ohm 2watt
R0306	302022	WI-SCH 10.00 OHM 2.00W 5%	1	resistor 10 Ohm 2watt
R0307	331969	WI-DR 0.56 OHM 5.00W 5%	1	resistor 0.56 Ohm 5watt
R0308	331969	WI-DR 0.56 OHM 5.00W 5%	1	resistor 0.56 Ohm 5watt
R0402	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0403	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0405	362479	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm/5watt
R0406	362479	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm/5watt
R0407	362479	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm/5watt
R0408	362479	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm/5watt
R0425	348593	WI-SO NTC 2.20 KOHM	1	safety component NTC
R0426	348593	WI-SO NTC 2.20 KOHM	1	safety component NTC
R0442	341713	WI-DR 4.70 OHM 4.00W 5%	1	resistor 4.70 Ohm 4watt
R0443	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt
R0484	332306	WI-SCH 3.30 KOHM 2.00W 5%	1	resistor 3.3k Ohm 2watt
R0485	332306	WI-SCH 3.30 KOHM 2.00W 5%	1	resistor 3.3k Ohm 2watt
S0001	349114	SCHALTER-NETZ	1	mains switch
VR102	348486	WI-TRI 47.00 KOHM LIN	1	pot trim 47k Ohm lin
VR103	357351	WI-SO WENDELPOTI 100 OHM	1	pot trim 100 Ohm
VR302	348486	WI-TRI 47.00 KOHM LIN	1	pot trim 47k Ohm lin

	112960	POWERMATE 1600-2 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
VR303	357351	WI-SO WENDELPOTI 100 OHM	1	pot trim 100 Ohm
	303576	SICHER-HALTE-FEDER	4	fuse clip
	328390	SICHER-HALTER FAU	1	fuse holder
	328391	SICHER-HALTER-KAPPE FEK	1	fuse holder carrier
	805038	PCB-- PM SERIE-2	1	pcb assy 80503
CN002	354230	STIFTLISTE 6POL TSW-106	2	connector male 6-pin
CN003	354230	STIFTLISTE 6POL TSW-106	1	connector male 6-pin
CN005	341937	MESSERLST. 4POL	1	connector male 4-pin
CN006	341937	MESSERLST. 4POL	1	connector male 4-pin
CN007	329022	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
C0001	346841	KO-EL 47.000MF 16V	1	cap electrolytic 47uF/16V
C0002	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0005	352307	KO-EL 10.000MF 16V	1	cap electrolytic 10uF/16V
C0006	352307	KO-EL 10.000MF 16V	1	cap electrolytic 10uF/16V
C0008	352307	KO-EL 10.000MF 16V	1	cap electrolytic 10uF/16V
C0009	337181	KO-FOL 0.010MF 100V 5%	1	cap mylar 10nF
C0011	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0014	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0015	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0016	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0017	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0020	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0025	352306	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0035	346841	KO-EL 47.000MF 16V	1	cap electrolytic 47uF/16V
C0038	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0039	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0040	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0041	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0047	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0051	352307	KO-EL 10.000MF 16V	1	cap electrolytic 10uF/16V
C0052	352307	KO-EL 10.000MF 16V	1	cap electrolytic 10uF/16V
D0003	362344	DISPLAY LED	1	display led
D0004	362344	DISPLAY LED	1	display led
D0005	362344	DISPLAY LED	1	display led
D0006	362344	DISPLAY LED	1	display led
X0001	358707	QUARZ-OSZIL-SMD 12.2880MHZ	1	crystal 12.288mhz